GON USER UNOTES

NO.14

\$2.50

SOFTWARE FEATURES	1
Kim banner program	JIM ZUBER
KIM DISASSEMBLER	
CHECK-OUT	ROBERT LARRABEE
LANGUAGE LAB	12
BASIC	
FOCAL	
TINY BASIC	
FORTH	
XPLØ	
SYM SECTION	18
ACCESSING THE SYM DISPLAYS	A.M. MACKAY
Wumpus & Music box mods	JIM ADAMS
AIM SECTION	19
Manual corrections	JODY NELIS
VIDEO & TVT-6	0.7
	23
	MIKE FIRTH
TVT-6 NOTES & RAM EXPANSION	MILAN MERHAR
CASSETTE STUFF	25
MAKE A SHORT CASSETTE T	TED BEACH
	CHRIS MCCORMACK
ANNOINCEMENTS & REVIEWS	27

From the feedback I've received concerning issue \$13, most of you were very happy about the "new" format so things will stay pretty much the same. A good number of comments specifically mentioned their satisfaction with the "language lab" so we may expand on it a bit in future issues. Lots of good stuff in store for you BASIC, FOCAL and TINY BASIC users. Thanks to all of you who responded to my questions on modifying BASIC to skip the initialization messages. As you will soon know, that question and many others will be answered in this issues' BASIC column. Also, thanks to Dick Grabowski of HDE and Bob Kurtz of Micro-Z, we now have a new command for BASIC.

A number of you have been asking for some 'terminal-oriented software so we have modified the original APPLE disassembler for the KIM. You'll need more memory, but if you have a terminal you're finding that out anyway.

Those of you with hard copy will no doubt enjoy the BANNER program. The present character set is designed for a 40 column printer but can easily (?) be re-designed for wider terminal widths. When you do come up with a new character set, send it in so the rest of us can enjoy it. Send it in on a cassette to make life easier for us and we'll publish it and/or offer it on cassette, depending on its design. There's enough info in the article to enable you to design your own character set and further info can be gotten from the Kilobaud article.

SUBMITTING ARTICLES

Since all articles will be retyped they need only be readable. Typing it would, of course, guarantee readability. Program listings, on the other hand, may not be retyped so, if at all possible, use white paper and a fresh ribbon on your printer. If there's no way you can generate an original source listing, then a handwritten source listing with MOS mnemonics, and labels of up to six characters, (don't forget to use labels when referencing zero page locations) will be satisfactory. Comments should be preceded by a semi-colon.

This will make it easy for me to assemble your program for publication. Disassembler output is not very satisfactory except when heavily commented, labeled and all zero page registers identified by name.

Perhaps the best way to submit program source listings would be to send a cassette of the assembler source file and I can then assemble it and run a listing on my Decwriter. I Can assemble source files from either the Micro-ade assembler (Peter Jennings) or the MOS/ARESCO/HDE assemblers. If you send a S.A.S.E.,I'll return your cassettes. It would be wise to dump two copies of the file to cassette just in case.

I can read most of the Hypertape-recorded cassettes I receive once I adjust the azimuth of the cassette head for the highest audio level while reading the program. I think this head adjustment problem has probably accounted for most of the tape interchange problems I've been aware of. The machines I use to make the newsletter cassettes have been adjusted as close as possible and 30 seconds of synch characters precede the program for setting up your equipment. So far, we have not had any cassettes returned, so we must be doing something right.

@ COPYRIGHT 1979 Eric C. Rehnke

BACK ISSUE AVAILABILITY

"Official" reprints of USER NOTES 1-12 are now available from Mark Kantrowitz, 15 Midway Ct., Rockaway NJ 07866. Prices are \$5.00 for issues 1-6 or 7-12 (1st Class in N America) - \$10.00 for issues 1-12 (1st Class in N America) - \$13.00 for issues 1-12 (overseas) U.S. Funds only.

LET THE BUYER BEWARE!!

Those of you who have been around this industry for awhile know by now that just 'cuz somethings advertised doesn't mean that it really exists.

I am very interested in hearing about your experiences with any of the advertisers in USER NOTES.

When purchasing hardware or software, it makes alot of sense to purchase the documentation ahead of time to see what you're getting into. The quality of documentation can, prove to be a good indicator of the company's performance in other areas pertaining to that product.

On the other hand, do be reasonable. Don't expect a 60 page manual to accompany a \$5 or \$10 software package. I'm really referring to products of medium or high complexity such as some Assemblers or high-level languages, floppy-disc drives, prom programmers, video boards etc.

For instance, are there detailed instructions for getting the product running on your system? Does the product need some non-standard hardware or software? Are there enough examples to make operation fairly straightforward? What if you have problems? Are there some trouble shooting hints in the manual? How 'bout a phone number to call if you have problems which you can't handle? For items which may cost from several hundred to several thousand dollars, it would be a good idea to call the company with some real or made-up questions just to see what kind of response you get.

Are you treated courteously? Do you get connected to someone who can answer your question? (If the right person doesn't happen to be in the office when you call, don't expect them to return a long distance call.)

It can get pretty lonesome out there when you've got a product that isn't performing and a company that ignores you. It's better to find out in advance how a company treats its customers. If something breaks, how will they back you up?

When you shop around for something big (like a floppy, for example) you should understand that price alone should not be THE determining factor. Other things to consider include: What kind of software comes with it? Will it interface easily with the particular high-level language I will want to use? What kinds of software can be used with it-any optional packages from the manufacturer? Can I interface the floppy system easily to some non-standard hardware I may want to add? How easy will it be to incorporate some improved software which gets released at a later date from the manufacturer?

(RAM based software that is brought in by means of a simple bootstrap program is generally much easier to upgrade than a ROM based operating system). Can the system software be backed-up on an extra disc? What will the manufacturer be offering in the next year or so? Do his plans sound reasonable? What else has he done? Past performance generally indicates future performance. If you're looking for the "cheapest" product-keep in mind that the manufacturer of the "cheapest" product probably can't afford to support his product next year. INVESTIGATE FULLY BEFORE YOU BUY!!!!!!

KIMSI USERS

Apparently Forethought Products, makers of KIMSI, have given up any plans to put out a newsletter of KIMSI information. I know there are alot of you out there so how 'bout if we have a section of USER NOTES just for you?

⁶⁵⁰² USER NOTES is published bimonthly by Eric C. Rehnke (POB 33093, N. Royalton, Ohio 44133 (216-237-0755)). Subscription rates for Volume 3 are \$13.00 (US and Canada) and \$19.00 elsewhere. No part of 6502 USER NOTES may be copied for commercial purposes without the express written permission of the publisher. Articles herein may be reprinted by club newsletters as long as proper publication credit is given and the publisher is provided with a copy of the publication.

SOFTWARE FEATURES

Jim Zuber 20224 Cohasset #16 Canoga Park, Ca 91306

If your KIM, SYM, or AIM system is hooked up to a printer or teletype get ready to have some fun! In the January 1979 issue of Kilobaud there was an article on page 64 called "Say it with Ban-. This program prints out giant characters on your printer. There were three problems with the

- It is written in 8080 code.
- 2. It uses octal notation.3. It uses almost 8K of memory.

I took the general concept of printing large characters and wrote an orginal program that has the following features:

- 1. Written in 6502 code.
- 2. I/O independent.
- 3. Uses HEX notation.
- 4. Only uses 2K of memory.
- 5. Relocatable data tables.
- 6. Easy user modification of character sets.

Let's talk about the I/O configuration first. Location 2004 and 2005 defines the \bar{I} nput character routine location for your system. If your terminal echos your input change 2003 to 4C. The character output routine location for your system is defined by locations 2007 and 2008. Your output routine must do the following:

- 1. Provide a line feed if necessary.
- 2. Provide null characters if necessary.
- 3. Must preserve the X, Y, and accumulator registers.

Text can be stored anywhere in memory and is defined by locations 200C and 200D. The text string can be as long as you want as long as you don't run out of memory. The data tables can be stored anywhere in memory as long as the starting address of the tables is stored in 2009 and 200A. SYM users will want to store the tables right after the program. The print character is defined in location 200B. Use the HEX equivalant of the ASCII character you want. The program is set up to use an @. I will explain later on how to make up your own characters or modify some of the ones I made up. To use the program start at 2000 and GO. You see a prompt (>>>). Type in the text you want You will

printed out. The program treats a carriage return as a space so take note. You terminate the text input with an @. If you typed in all valid characters you will see "@ o k" printed. Get your paper ready and type a carriage return to start the printing. If you type an illegal character you will see "@ " with the illegal characters sandwiched between the @ and the . Retype the text using only legal characters. At the end of the printout the program will prompt for more text. The legal characters are A thru Z, O thru 9, space, c/r, and the following characters: * - + : My characters are 10 rows by 35 columns. Obviously this is too big for the AIM printer. Don't worry, you can make up your own character set to work on the AIM. To create your own character set just follow these simple rules:

- 1. Always store ff at the end of the tables.
- 2. The first BYTE should be the HEX
- equivalent of the ASCII character. 3. The second BYTE should be the HEX number of data Bytes.
- 4. Carriage returns are defined by EE.
- 5. Store the configuration of the charac-
- ter in a serial manner.
 6. A "print spaces" data Byte is defined by Bit 7 being set to zero and Bits 0 thru 6 set to the number of spaces you want printed, Example: 07 would print 7 spaces.
- 7. To print a mark (or a character) set Bit 7 to one and Bits 0 thru 6 set to the number of marks. Example: 87 would print 7 @'s.

page 1

Maybe this will help you understand a little better. In order to print an "1" (one) that is 15 $\,$ columns by 7 rows wide, just put this in the tables: 31 OA EE EE 8F EE 8F EE 8F EE EE EE. The 31 is the HEX equivalent of ASCII character one. The OA is the number of data Bytes. Then I print 2 carriage returns, 3 rows of 15 characters and 2 more carriage returns. Hope you enjoy this program. If you want to modify any of my characters you can find their location by storing the character in 0004, then call the find character subroutine. The character's location plus 2 will be stored in 0000 and 0001.

0010	2000				#KIH-1	BANNER PROGRAM		
0015	2000				#WRITT	EN BY JIH ZUBER	12/23/78	
0020	2000							
0025	2000					*=\$ 0		
0030	0000				PNTL	*= * +1		
0035	0001				PNTH	*=*+1		
0040	0002				BUF1	*= * +1		
0045	0003				BUF2	* = * +1		
0050	0004				TEMP	*= *+1		
0055	0005				TEMPX	* = * +1		
0060	0006				TEMPY	* = * +1		
0065	0007							
0070	0007				#KIM I	/0		
0075	0007				BETCH	=\$1E5A		
00B0	0007				OUTCH	=\$1EA0		
0085	0007				CRLF	=\$1E2F		
0090	0007							
0095	0007				E08	=\$40	FEND OF STRING CHAR	
0100	0007							
0105	0007					*=\$2000		
0110	2000	4C	0E	20	STAR	JMP OVER		
0115	2003	4C	2C	21	INV	JMP INPT	FINPUT ROUTINE	
0120	2006	4C	34	21	OUTV	JMP OUTC	FOUT VECTOR	
0125	2009	00			TBLL	.BYTE \$00	FTABLE LOW	
0130	200A	30			TBLH	.BYTE 430 22	FTABLE HIGH	
0135	200B	40			PRCH	.BYTE \$40	PRINT CHAR	
0140	200C	00			BUFL	BYTE \$98 50	BUFFER LOW	
0145	200D	40			BUFH	BYTE \$40 21	BUFFER HIGH	
0150	200E					•		
0155	200E	D8			OVER	CLD		
0160	200F	AO	00			LDY #0		
0165	2011	20	FA	20		JSR INTB	FINPUT TEXT	
0170	2014	A9	3E			LDA #'>	FROMPT CHAR	
0175	2016	20	06	20		JSR OUTV		
01B0	2019	20	06	20		JSR OUTV		
0185	201C	A9	OD			LDA #\$OD	SEND A CR	
0190	201E	20	06	20		JSR DUTV		

0000000000000000000000	0195	2021	20 03	20	CHAR	JSR INV	FINPUT STRING
888888888888888888888888888888888888888	0200	2024	91 02			STA (BUF1),Y	
86566666666666666666666666666666666	0205	2026	C9 40			CMP DEDS	FEND OF STRING?
656566666666666666666666666666666666666	0210	2028	FO 06			BEO CHEK	AEMD OL SIKTURE
35555 5566	0215	202A	20 10	21		JSR INCB	
08888 08888	0220	202D	4C 21				
6686 68686	0225	2030		20	CHEK	JMP CHAR	
866666666666666666666666666666666	0230	2033	AO 00	20	CHEK	JSR INTB	ICHECK CHARS
000000000000000000000000000000000000000	0235	2035			LOP3	LDY #Q	
		-	B1 02			LDA (BUF1),Y	
	0240	2037	C9 40			CMP #EOS	#END STRING?
	0245	2039	FO 17			BEQ OK	
	0250	203B	85 04			STA TEMP	
	0255	203D	20 C9	20		JBR FDCH	#FIND CHAR
58988	0260	2040	C9 FF			CMP OSFF	∮IS IT BAD?
66666 55666	0265	2042	DO 08			BNE LOP4	
65656 66666 6656	0270	2044	A5 04			LDA TEMP	
66666 6666 6666							
66666 66666 6666	0275	2046	20 06			JSR DUTV	FSTART OVER
86666 66666 6666	0280	2049	4C 00			JMP STAR	
88888 88888 88688	0285	204C	20 10		LOP4	JBR INCB	
000000000000000000000000000000000000000	0290	204F	4C 33	20		JMP LOF3	
000000000000000000000000000000000000000	0295	2052	A9 4F		OK	LDA #'0	PROMPT "OK"
000000000000000000000000000000000000000	0300	2054	20 06	20		JSR DUTV	
	0305	2057	A9 4B			LDA ♦'K	
	0310	2059	20 06	20		JSR OUTV	
	0315	205C	A9 OD			LDA #\$OD	
000000000000000000000000000000000000000	0320	205E	20 06	20		JSR DUTV	
000000000000000000000000000000000000000	0325	2061		20		JSR INV	#WAIT FOR KEY
0666666	0330	2064	20 FA	20		JSR INTB	FREADY TO PRINT
88888888	0335	2067	AO 00		LOP6	LDY #0	
8888888	0340	2069	B1 02			LDA (BUF1),Y	
88888888	0345	206B	C9 40			CMP #EGS	#END?
8888888888888	0350	206D	DO 03			BNE LOP7	
22222222	0355	206F	4C 00	20		JMP STAR	
800000000	0360	2072	85 04		LOP7	STA TEMP	
000000000000000000000000000000000000000	0365	2074	20 C9	20		JSR FDCH	FIND CHAR
40000000000000000000000000000000000000	0370	2077	20 BB			JSR PNTC	#PRINT IT
	0375	207A	A9 OD			LDA #\$OD	3 ROWS
	0380	207C	20 06	20		JSR OUTV	70 1043
	03B5	207F	20 06			JSR OUTV	
000000000000000000000000000000000000000		2082					
000000000000000000000000000000000000000	0390		20 06			JSR DUTV	ATMC BUEFFD
86666666	0395	2085	20 10			JSR INCB	INC BUFFER
0000000	0400	2088	4C 67	20		JMP LOP6	
88888888	0405	208B			DUTO	1 DV 40	ADDIVIT DUAG
00000000	0410	208B	A0 00		PNTC	LDY #0	PRINT CHAR
38330333	0415	208D	B1 00			LDA (PNTL),Y	\$SUBROUTINE
2222222	0420	208F	C9 EE			CMP #\$EE	FTIME TO CARRIAGE RETURN?
000000000000000000000000000000000000000	0425	2091	DO 08			BNE LP10	
066666666666666666666666666666666666666	0430	2093	A9 OD			LDA #\$OD	FOUTPUT C/R
	0435	2095	20 06			JSR OUTV	
	0440	2098	4C BF	20		JMP STOP	
	0445	209B	85 04		LP10	STA TEMP	#GET DATA
888666666666666666666666666666666666666	0450	209D	29 80			AND #\$80	#MARK OR SPACE
00000000000000000000000000000000000000	0455	209F	DO OD			BNE MARK	
888888888888888888888888888888888888888	0460	20A1	A4 04			LDY TEMP	FMUST BE SPACE
88888 88888	0465	20A3	A9 20		LP11	LDA #\$20	FOUTPUT SPACE
00000 00000	0470	20A5	20 06	20		JSR DUTV	
88888 88888	0475	20A8	88			DEY	
88888 88888	0480	20A9	FO 14			BEQ STOP	#ANY MORET
8888888888888888888888888888888888888	04B5	20AB	4C A3 :	20		JMP LP11	∮MUST BE
000000000000000000000000000000000000000	0490		A5 04		MARK	LDA TEMP	#MUST BE MARK
000000000000000000000000000000000000000	0495	20B0	29 7F			AND #\$7F	#MASK BIT 7
	0500	20B2	A8			TAY	
	0505	20B3	AD OB	20	LP12	LDA PRCH GET	PRINT CHAR
	0510	20B6	20 06 3	20		JSR OUTV	JOUTPUT MARK
666666666 66666666666666666666666666666	0515	20 B9	88			DEY	
000000000000 00000000000000000000000000	0520	20BA	FO 03			BEG STOP	JANY MORE?
000000000000000000000000000000000000000	0525	20BC	4C B3	20		JMP LP12	MUST BE
88888 68866 68688	0530	20BF	CA		STOP	DEX	CHECK END
00000 00000 00000	0535	20C0	FO 06			BEQ LP13	
2000 00000 00000							
86860 88888 8888	0540	2002	20 1E			JSR INCP	FINC POINTER
000000000000000000000000000000000000000	0545	20C5	4C BB	20		JMP PNTC	#GO BACK
202000000000000000000000000000000000000	0550	20CB	60		LP13	RTS	
000000000000000000000000000000000000000	0555	20C9					
	0560	20C9	20 05	21	FDCH	JSR INTP	FIND CHARACTER
	0565	20CC	AO 00		LOP1	LDY #0	;SUBROUITNE
	0570	20CE	B1 00			LDA (PNTL),Y	#PICK UP ILLEGAL?
	0575	20D0	C9 FF			CMP ##FF	
	0580	20D2	FO 1B			BEQ OUT	
	0585	20D4	C5 04			CMP TEMP	FRIGHT ONE?
	0590	20D6	FO 1B			BEQ OUT1	
	0575	20D8	C8			INY	#MUST NOT BE
	0600	20D9				LDA (PNTL),Y	BYTE COUNT
	0605		18			CLC	
	0610		45 00			ADC PNTL	SADD TO POINTER
	0615		85 00			STA PNTL	
	0620	20E0	A9 00			LDA #0	
	0625		65 O1			ADC PNTH	
		20E4	B5 01			STA PNTH	
	0470					- · · · · · · · · · · · · · · · · · · ·	
	0630		20 1F	21		JSR INCP	
	0635	20E6	20 1E 20 1E			JSR INCP JSR INCP	
•	0635 0640	20E6 20E9	20 1E	21		JSR INCP	\$LOOK AGAIN
	0635 0640 0645	20E6 20E9 20EC	20 1E 4C CC	21	OUT	JSR INCP JMP LOP1	\$LOOK AGAIN
	0635 0640	20E6 20E9	20 1E	21	OUT	JSR INCP	\$LOOK AGAIN

```
0655
       20F0
              20 1F 21
                            OUT 1
                                    ISR THEP
                                                      FLOOK AT DATA
 0660
       20F3
              B1 00
                                    LDA (PNTL),Y
 0665
       20F5
              AA
                                    TAX
                                                      #BYTE IN X
 0670
       20F6
              20
                 1E 21
                                    JSR INCP
 0675
       20F9
              60
                                    RTS
 0480
       20FA
 0685
       20FA
              AD OC 20
                            INTB
                                   LDA BUFL
                                                      SINITIAL TZE
 0690
       20FD
              85 02
                                   STA BUF1
                                                      #BUFFER SUB
 0695
       20FF
              AD OD 20
                                   I DA RIIFH
0700
       2102
              B5 03
                                   STA BUE2
0705
       2104
              60
                                   RTS
0710
       2105
0715
       2105
              AD 09 20
                           INTP
                                   I DA TRII
                                                      INITIAL 17F
0720
       2108
              85 00
                                   STA PNTI
                                                      #POINTER SUB
0725
       210A
              AD 0A 20
                                   LDA TBLH
0730
       210D
              85 01
                                   STA PNTH
       210F
0735
              60
                                   RTS
0740
       2110
0745
       2110
              18
                           INCB
                                   CLC
                                                     #INCREMENT
0750
       2111
              A5 02
                                   LDA BUF1
                                                      #BUFFER SUR
0755
       2113
              69
                 01
                                   ADC ##1
0760
       2115
              85 02
                                   STA BUF1
0765
       2117
              A5
                 03
                                   LDA BUF2
       2119
0770
              69 00
                                   ADC #0
0775
       211B
              85
                 03
                                   STA BUF2
0780
       211D
              60
0785
       211E
0790
       211E
                           INCP
                                   CLC
                                                     JINCREMENT
0795
       211F
              A5 00
                                   LDA PNTL
0800
      2121
              69 01
                                   ADC #1
                                                     #PDINTER SUB
0805
      2123
             85 00
                                   STA PNTL
0810
      2125
             A5 01
                                   LDA PNTH
       2127
0815
              49
                00
                                   ADC #0
      2129
0820
              85 01
                                       PNTH
                                   STA
0825
      212B
             60
                                   RTS
0830
       2120
             84 06
0835
       212C
                           INPT
                                   STY
                                       TEMPY
                                                     SAVE Y
      212E
0840
             20 5A 1E
                                   JSR GETCH
                                                     FBET A CHAR
0845
       2131
              A4 06
                                   LDY
                                       TEMPY
0850
       2133
              60
       2134
0855
              48
                           DUTC
                                                     SAVE CHAR
0860
       2134
                                   PHA
      2135
             86 05
                                   STX TEMPX
                                                     FAND X AND Y
0865
0870
      2137
             84 06
                                   STY
                                       TEMPY
0875
       2139
             C9
                OD
                                       #$0D
                                                     FIS IT A C/R7
             DO 04
0880
      213B
                                   BNE CONT
0885
      213D
             20
                2F
                    1E
                                   JSR
                                       CRLF
0890
      2140
             4C
                46
                    21
                                   JMP RESTOR
                                                     FGET BACK THE REGS AND RETURN
0895
      2143
             20
                A0 1E
                           CONT
                                   JSR DUTCH
                                                     FOTHERWISE USE KIM OUTPUT.
0900
      2146
             A6
                05
                           RESTOR
                                  LDX
                                       TEMPX
0905
      2148
             A4 06
                                   LDY
                                       TEMPY
                                                     *RETORE THE ACC.
0910
      214A
             AR
                                  PLA
0915
      214B
             40
                                  RTS
                                                     FAND RETURN
                           FINISH .END
0920
      214C
```

```
EE EE EE EE EE EE EE 41 20 A3 EE A3 EE A3
2200
                                                                 84 EE 84 1B 84 EE A3 EE A3 EE 50 23 A3 EE A3 FE
                                                          2400
2210
      EE OF 85 OA 85 EE OF 85 OA 85 EE OF 85 OA 85 EE
                                                                       11 85 08 85 EE 11 85 08 85 EE 11 85 08 85
                                                          2410
                                                                 A3 EE
                                                     A3
2220
      0F
         85
            0A 85 EE A3 EE A3 EE
                                  A3 EE 42
                                           2B
                                              A3 EE
                                                          2420
                                                                       85
                                                                          08
                                                                             85 EE
                                                                                   11
                                                                                      92
                                                                                          ΕE
                                                                                             11
                                                                                                92 EE 11
                                                                                                         92
                                                                                                            FF
                                                                                                                51
2230
      EE A3
            EE 85 0A 85 0A 85 EE 85 0A 85 0A 85 EE
                                                     25
                                                          2430
                                                                 20 A3
                                                                                      84
                                                                                                   84 EE
                                                                             EE 84
                                                                                   1 B
                                                                                         EE
                                                                                             84
                                                                                                1 B
                                                                                                         84
                                                                                                            1 B
                                                                                                                84
      0A 85 0A 85 EE 85 0A 85 0A 85 EE 01 A1 EE 03
                                                                 EE 84
2240
                                                     80
                                                          2440
                                                                       02
                                                                          84
                                                                             15 84 EE A3 EE A3
                                                                                                EE 04 84
                                                                                                         EE
                                                                                                            02
                                                                                                                84
2250
      03 BD EE 04 BB 05 BB EE 43 22 A3 EE
                                           A3 EE
                                                  A3 EE
                                                          2450
                                                                 EE 52
                                                                       21 A3 EE A3 EE A3 EE 11 85 08 85 EE
                                                                                                                85
                                                                                                            11
      85 19 85 EE 85 19 85 EE 85 19 85 EE
                                           85 19
                                                  85
2260
                                                     EE
                                                                 08 85 EE
                                                                          11 85 08 85 EE 96 08 85 EE A3 EE
                                                          2460
                                              1F
      88 13 88 EE 88 13 88 EE 88 13 88 EE
                                                  A3
2270
                                           44
                                                     EE
                                                          2470
                                                                 EE 11 92 EE 53 36 04 81 OF 8B EE 03 82 OE 8D
      A3 EE A3 EE 85 19 85 EE 85 19 85 EE
                                           85 19 85 EE
2280
                                                          2480
                                                                 01 84 0D 90 EE 85 0B 85 09 85 EE 85 0B
                                                                                                         85
                     9F EE 03 9D EE 04
                                               45 2C
            85 EE 02
                                        9B
                                           EE
      85 19
2290
                                                          2490
                                                                 EE 85 0B 85 09 85 EE 85 0B 85 09 85 EE 01 93
      EE A3 EE A3 EE 85 OA 85 OA 85 EE 85 OA
22A0
                                                          24A0
                                                                 84 EE 03 8F 0C 82 EE 04 8D 0D 81 EE
                                                                                                      54
                                                                                                         19
                                                                                                            EE
                                                                                                                1E
      EE 85 0A 85 0A 85 EE 85 0A 85 0A 85
                                           EE 85 0A 85
                                                          24B0
22B0
                                                                 85 EE 1E 85 EE 1E 85 EE A3 EE A3 EE A3
      OA 85 EE 85 19 85 EE 85 19 85 EE 46
                                           25 A3 EE A3
                                                          2400
2200
                                                                 EE 1E 85 EE 1E 85 EE 55 14 A3 EE A3 EE
                                                                                                         A3
                                                                                                               85
      EE A3 EE OF 85 OA 85 EE OF 85 OA 85 EE OF 85 OA
                                                          24B0
22D0
                                                                 EE 85 EE 85 EE 85 EE A3 EE A3 EE
                                                                                                         56
                                                                                                            1 C
                                                                                                               18
      85 EE OF 85 OA 85 EE OF 85 OA 85 EE 1E 85 EE 1E
                                                          24F0
                                                                 8B EE 11 BA EE 0B 89 EE 05 89 EE 88 EE
22E0
                                                                                                         88
      85 EE 47 26 A3 EE A3 EE A3 EE 85 19 85 EE 85 19
                                                                 89 EE OB 89 EE 11 8A EE 18 8B EE 57 18 A3 EE
                                                          24F0
22F0
      85 EE 85 08 84 0D 85 EE 85 08 84 0D 85 EE 91
                                                                 EE 8A EE 07 8D EE 11 92 EE 11 92 EE 07 8D EE 8A
2300
                                                     OA
                                                          2500
      88 EE 91 OA 88 EE 91 OA 88 EE 48 18 A3 EE A3 EE
                                                                 EE A3 EE A3 EE 58 2C 88 15 86 EE 05 86 OF 86
2310
                                                          2510
                                                                                                               EE
                     OF 85 EE OF 85 EE OF
                                           85 EE A3 EE
      A3 EE OF
               85 EE
                                                          2520
                                                                 08 86 09 86 EE 0B 86 03 86 EE 0E 89 EE 0E 89 EE
2320
      A3 EE A3 EE 49 1F EE 85 19 85 EE 85 19 85 EE 85
                                                                 OB 86 03 86 EE 08 86 09 86 EE 05 86 OF
                                                          2530
2330
                                                                                                         86 EE 88
         85 EE A3 EE A3 EE A3 EE
                                  85 19
                                        85
                                               85 19
                                                     85
                                                                15 86 EE 59 1C 1A 89 EE 17 88 EE 14 86 EE 12 85 EE 94 EE 94 EE 12 85 EE 14 86 EE 17 88 EE 1A 89
      19
                                                           2540
2340
      EE 85 19 85 EE 4A 1A 04 87 EE 03 88 EE 02 89 EE
                                                           2550
2350
      84 EE 84 EE 84 EE 84 EE 02
                                  A1 EE
                                        03 A0 EE 04
                                                     9F
                                                          2560
                                                                    5A
                                                                       34 86 18 85 EE 89 15 85 EE 85 01 86 12 85
2360
                                                                 EE
            2A A3 EE A3 EE OF 85 EE OD 84 01 84 EE OB
                                                                EE 85 04 86 OF 85 EE 85 07 86 OC 85 EE 85 0A 86
                                                           2570
2370
      EE 4B
      84 05 84 EE 09 84 09 84 EE 07 84 OD 84 EE 05 84
2380
                                                           2580
                                                                 09 85 EE 85 0D 86 06 85 EE 85 10 86 03 85 EE 85
      11 84 EE 03 84 15 84 EE 01 84 19 84 EE 4C 14 A3
                                                           2590
                                                                 13 8B
                                                                      EE 85 16 88 EE 30 1C
2390
                                                                                            A3 EE A3 EE
                                                                                                         A3 FE 85
         A3 EE A3 EE 85 EE 85 EE 85 EE 85 EE 85
23A0
      EE
                                                           25A0
                                                                 19 85
                                                                      EE 85 19
                                                                                85 EE 85 19 85 EE 85 19
                                                                                                         85 EE A3
      EE 85 EE 4D 18 A3 EE A3 EE 17 8C EE OC 8E EE 8F
                                                           25B0
23B0
                                                                EE A3
                                                                      EE A3 EE
                                                                                31 OD EE EE EE A3 EF A3
                                                                                                         EE
                                                                                                            A3 FF
2300
      EE 8F
            EE OC 8E EE 17 8C EE A3 EE A3 EE 4E 19 A3
                                                           25C0
                                                                EE EE EE EE 32
                                                                                30
                                                                                   94 0A 85 EE 94 0A 85
                                                                                                            94
                                                                                                         FF
                                                                                                               OA
      EE A3 EE 1A 89 EE 13 8A EE OD 89 EE OD 89 EE 06
                                                           25D0
                                                                85 EE 85 0A 85 0A 85 EE 85 0A 85 0A 85
23D0
                                                                                                         EE 85 0A
      89 EE 89 EE A3 EE A3 EE 4F 20 A3 EE A3 EE 84 1B
                                                           25E0
                                                                85 0A
                                                                      85 EE 85 OA 85 OA 85 EE 85 OA 94
23E0
                                                                                                               0A
                                                                                                         EE
                                                                                                            85
      84 EE 84 1B 84 EE 84 1B 84 EE 84 1B 84 EE 84 1B
                                                                94 EE 85 OA 94 EE 33 30 85 OA 85 OA 85 EE 85 OA
23F0
```

2600 85 OA 85 EE 85 OA 85 OA 85 EE A3 EE A3 EE A3 EE 34 1B 10 93 EE 10 93 EE 5410 3420 3430 10 93 EE 10 85 EE 10 85 EE 10 85 EE A3 EE A3 EE A3 EE 10 85 EE 35 30 85 0A 94 EE 85 0A 94 EE 85 3440 OA 94 EE 85 OA 85 OA 85 EE 85 OA 85 OA 85 EE 85 3450 OA 85 OA 85 EE 85 OA 85 OA 85 EE 94 OA 85 EE 94 3460 3470 OA 85 EE 94 OA 85 EE 36 2A A3 EE A3 EE A3 EE 85 08 85 OC 85 EE 85 08 85 OC 85 EE 85 08 85 OC 85 3480 EE 85 08 85 0C 85 EE 92 0C 85 EE 92 0C 85 EE 92 0C 85 EE 92 0C 85 EE 18 88 EE 18 88 EE 18 88 EE 18 85 EE A3 EE A3 EE A3 EE 3490 34A0 34B0 38 24 A3 EE A3 EE A3 EE 85 OA 85 OA 85 EE A3 EE A3 EE A3 EE 39 23 11 92 EE 11 92 EE 11 92 34C0 3400 34E0 EE 11 85 08 85 EE 11 85 08 85 EE 11 85 08 85 EE 34F0 3800 11 85 08 85 EE A3 EE A3 EE A3 EE OD 07 EE EE EE EE EE EE EE 2A 34 EE 09 82 06 82 06 82 EE 0B 82 3510 04 82 04 82 EE OD 82 02 82 02 82 EE OF 86 EE 09 3520 92 EE OF 86 EE OD 82 02 82 02 82 EE OB 82 04 82 3530 04 82 EE 09 82 06 82 06 82 EE 2E OD EE EE EE EE 3540 85 EE 85 EE 85 EE EE EE EE ED 1E OF 85 EE OF 3550 EE OF 85 EE 3540 85 EE OF 85 EE OF 85 EE 28 10 EE OF 85 EE OF

EDITORS NOTE: The disassembler program was originally written for the Apple and appeared in Doctor Dobbs Journal (Sept 76). It has been modified for KIM by Bob Kurtz and your editor. Bob Kurtz wrote the article.

KIM-1 "DISASSEMBLER" PROGRAM

Bob Kurtz Micro-Z Co P 0 Box 2426 Rolling Hills Ca 90274

PRELIMINARY:

The purpose of the disassembler is to take any program that has been entered into memory in the KIM-1, and to print-out an "object" code and a "source" code listing of this program - to permit analysis and modification, if desired. In a sense, it takes a completed program and reconstructs the assembly language format - or "disassembles" the program.

The following is a sample of the print-out format:

Address	O bject Code	Source Code
23BC-	E8	INY
23BD-	A9 53	LDA #53
23BF-	85 01	STA 01
23C1	91 7E	STA (7E),Y
23C3-	4C 64 1C	JMP 1C64

#DISASSEMBLER PROGRAM FOR THE 6502 #WRITTEN BY STEVE WOZNIAK & ALLEN BAUM #AND PUBLISHED IN DOCTOR DOBBS JOURNAL 0020 2000 0030 2000 0040 2000 #SEPT 1976 0050 2000 0060 2000 0070 2000 X=\$0 0072 0000 PCL ***=*+1** 0073 0001 PCH *=*+1 COUNT *=*+1 0075 0002 FORMAT *=*+1 0080 0003 LENGTH *= *+1 0090 0004 0100 0005 LMNEM *=*+1 0110 0006 RMNFM X=X+1 0142 0007 YSAVE *=*+1 0150 0008 0160 0008 #KIM I/O TO FOLLOW 0170 000B PRTBYT =\$1E3B 0180 OOOR OUTCH =\$1EA0 0190 0008 CRLE =\$1E2F CLEAR =\$1C64 0191 0008 0192 =\$1E9E 0008 OUTSP 0200 0008 0210 ***=\$2000** 0008 0211 2000 20 OF 20 START JSR DSMBL 0212 2003 20 9E 1E JSR OUTSP 0213 2006 20 9E 1E JSR OUTSP 0214 2009 20 9E 1E JSR OUTSP 0215 200C 4C 64 1C JMP CLEAR 0220 200F A9 OD DSMBL LDA #13 STA COUNT

3.7 3.080 3590 85 EE OF 85 EE O5 99 EE O5 99 EE O5 99 EE OF 85 EE OF 85 EE AA 16 EE EE EE EE O5 85 OD 85 EE 05 85 0D 85 EE 05 85 0D 85 EE EE EE EE 21 13 EE EE EE 85 03 9B EE 85 03 9B EE 85 03 9B EE EE EE EE 3B 16 EE EE EE EE 05 85 0E 85 EE 04 35A0 35B0 35C0 86 OE 85 EE 02 88 OE 85 EE EE EE EE 3F 27 17 8C EE 17 8C EE 17 8C EE 1E 85 EE 85 02 8B OC 85 EE 35D0 35E0 85 02 88 OC 85 EE 85 02 88 OC 85 EE OD 96 EE OD 35F0 96 EE OD 96 EE 24 30 02 85 08 92 EE 02 85 08 92 EE 02 85 08 92 EE 02 85 08 85 EE A3 EE A3 3600 3610 EE 02 85 08 85 08 85 EE 02 92 08 85 EE 02 92 08 85 EE 02 92 08 85 EE 2C OF EE EE EE EE 03 85 EE 02 86 EE 88 EE EE EE EE 28 16 EE EE EE A3 EE 3620 3630 3640 A3 EE A3 EE 85 19 85 EE 85 19 85 EE 85 19 85 EE 3650 29 16 85 19 85 EE 85 19 85 EE 85 19 85 EE A3 EE A3 EE A3 EE EE EE EE EE FF CD 00 40 5E 40 CO 30 3660 3670 4E 1A 40 40 CF 75 C4 B2 4F 6F 46 00 56 76 06 00 96 75 52 40 DF C6 76 A0 6E 77 04 42 5F FF C6 80 3680 3690 15 3E 40 44 57 F4 07 37 F6 4F 40 04 6B EE E7 02 36A0 F7 E2 40 30 86 37 C3 05 C7 76 62 01 96 9F E6 62 ORAE 47 5D 44 01 76 23 04 61 47 D3 02 01 B2 3E 00 00 97 F6 12 A0 F7 D7 40 00 97 6C 82 40 E7 F6 00 88 3600 36D0 B7 64 44 21 BA OE 02 01 OF FD 00 01 A9 C1 00 00 36E0 FF FE 06 CO 76 F5 C6 D0 FF D6 00 40 A7 FC 42 60 3450 258 6-13

The Address and Object Code columns are the standard listings for the program under scrutiny. You will notice that the disassembler has arranged the code listing by one, two, or three byte commands and has printed the address column accordingly.

The Source Code columns contain the MOS Technology 650X Mnemonic abbreviations for the command - and the Operand listing. The following is an explanation of the address mode for the various operands:

Operand	Address Mode
blank	Accumulator, Implied
#53	Immediate
01	Zero Page
01,X 01,Y	Zero Page, indexed by X or Y
(7E),Y	Indirect Indexed
(7E,X)	Indexed Indirect
1C64	Absolute of Branch
(1C64)	Indirect
1C64,X	Absolute (indexed by X)
1C64,Y	Absolute (indexed by Y)

PROCEDURE:

- 1. Load the starting address of the program to be disassembled into locations 0000 (Low byte) and 0001 (High byte).
- 2. Go to location 2000
- 3. Press "G" on terminal

The "disassembler" will now print-out the first 13 commands of the program under scrutiny. At the end of this print-out, simply press "G" again and the next 13 commands will be printed out. Continuing to press "G" whenever the program stops, will step you through the entire program under investigation.

The program stops after each 13 commands. If you wish to modify this, change the byte in location 2010 from \$0D (13 decimal) to any number up to SFF (256 decimal).

If portions of the disassembled program do not appear to make sense, these may be "look-up" tables within the program. As an example, the disassembler can be used to "disassemble" the disassembler program! Addresses \$2000 to \$211A will print out properly since these contain the body of the program commands. However, locations \$211B to \$21F9 contain the tables for all the mnemonics and symbols and will print-out gibberish.

FCOUNT FOR 13 INSTR. DSMBLY.

2011

85 02

```
0240
      2013
             20 21 20
                          DSMBL2 JSR INSTDS
                                                    DISASSEMBLE AND DISPLAY INSTR.
0250
      2016
             20 FC 20
                                  JSR PCADJ
                                                    SUPPORTE POLIN TO NEXT INSTR.
0260
      2019
             85 00
                                  STA PCL
             84 01
                                  STY PCH
0270
      201B
                                                    DONE FIRST 19 INSTR?
0280
             C6 02
                                  DEC COUNT
      201D
0290
      201F
             DO F2
                                  BNE DSMBL2
                                                    PRINT PCL.H
0300
      2021
             20 E2 20
                          INSTDS
                                  JSR PRPC
             A1 00
                                                    AGET OPCODE
                                  LDA (PCL+X)
0310
      2024
0320
      2026
             A8
                                  TAY
0330
      2027
             44
                                  LSR
                                                    #EVEN/ODD TEST
0340
      2028
             90 OB
                                  BCC IEVEN
                                  LSR
                                                    STEST RIT 1.
0350
      202A
             4A
                                                    *XXXXXX11 INSTR. INVALID.
                                  BCS ERR
0360
      202B
             BO 17
                                  CMP
                                      *$22
0370
      202D
             C9
                22
                                                    $10001001 INSTR. INVALID.
$MASK 3 BITS FOR ADDRESS MODE &
0380
      202F
             FO 13
                                  REG ERR
0390
      2031
             29 07
                                  AND #$7
                                                    ;ADD INDEXING OFFSET.
;LSB INTO CARRY FOR
0400
      2033
             09 80
                                  DRA #$80
                          IEVEN
0410
      2035
             44
                                  LSR A
                                                    FLEFT/RIGHT TEST BELOW.
FINDEX INTO ADDRESS MODE TABLE.
0420
      2036
             AA
                                  TAX
                                  I DA MODE.Y
0430
      2037
             BD 1B 21
                                                    FIF CARRY SET USE LSD FOR
0440
      203A
             BO 04
                                  BCS RIMODE
                                                    *PRINT FORMAT INDEX
      203C
             4A
                                  LSR A
0450
                                  ISR A
0460
      203D
             4A
                                                    FIF CARRY CLEAR USE MSD.
                                  LSR A
0470
      203E
                                  ISR A
0480
      203F
             4A
                                                    #MASK FOR 4-BIT INDEX
                          RTMODE AND #$F
      2040
             29 OF
0490
                                                    $50 FOR INVALID OF CODES.
                                  BNE GETFMT
      2042
             DO 04
0500
                                                    SUBSTITUTE $80 FOR INVALID OF,
                                      *$80
      2044
             A0 80
                          FRR
                                  LDY
0510
                                                     SET PRINT FORMAT INDEX TO O
                                      #$0
                                  LDA
0520
      2046
             A9 00
                          GETEME
0530
      2048
             ΔΑ
                                  TAX
                                                    FINDEX INTO PRINT FORMAT TABLE.
                                      MODE2.X
             BD 5F 21
                                  LDA
0540
      2049
                                  STA
                                      FORMAT
             85 03
0550
      204C
                                                    #MASK 2-BIT LENGTH. 0=1-BYTE
                                  AND
             29
0560
      204E
                03
                                  STA LENGTH
                                                    $1=2-BYTE, 2=3-BYTE.
             85 04
0570
      2050
                                                    OP CODE.
                                  TYA
      2052
             98
0580
                                                    #MASK IT FOR 1XXX1010 TEST.
                                  AND #$BF
      2053
             29 8F
0590
                                                    SAUF IT.
      2055
                                  TAX
0600
             AA
                                                    FOR CODE TO 'A' AGAIN.
      2056
                                  TYA
0610
             98
             AO 03
                                  LDY #$3
      2057
0620
                                  CPX #$8A
                88
      2059
             E0
0630
                                  BEQ MNNDX3
      205B
             F0
0640
                           MNNDX1 LSR A
0650
      205D
             4A
                                                    FORM INDEX INTO MNEMONIC TABLE.
             90 08
                                  BCC MNNDX3
0660
      205E
                                  LSR A
0670
      2060
             4A
                                                     ;1XXX1010 -> 00101XXX
             4A
                           MNNDX2 LSR A
0880
      2061
                                                     ;XXXYYY01 -> 00111XXX
                                  ORA
                                       #$20
0690
       2062
             09
                20
                                                     XXXYYY10 -> 00110XXX
0700
       2064
             88
                                  DEY
                                                     ;XXXYY100 -> 00100XXX
                                  BNE MNNDX2
0710
      2065
             DO FA
                                                     *XXXXX000 -> 000XXXXX
                                  TNY
0720
      2067
0730
       2068
                           MNNDX3 DEY
             88
                                  BNE MNNDX1
             DO F2
0740
       2069
                                                     SAVE MNEMONIC TABLE INDEX.
0750
             48
                                  PHA
       206B
                           PROP
                                  LDA (PCL),Y
0760
       206C
             B1 00
                                   JSR PRBYT
0770
       206E
             20
                13 21
                                   LDX #$1
       2071
             A2 01
0780
                                  JSR PRBL2
             20 F3 20
                           PROPBL
0790
       2073
                                                     PRINT INSTR (1 TO 3 BYTES)
                                   CPY LENGTH
0800
       2076
             C4 04
                                                     ; IN A 12 CHARACTYER FIELD.
                                   INY
       2078
             C8
0810
                                   BCC PROP
       2079
             90 F1
0820
                                                     #CHAR COUNT FOR MNEMONIC PRINT.
                                   LDX #$3
       207B
             A2 03
0830
                                   CPY
                                       #$4
       207D
             CO 04
0840
                                   BCC PROPEL
0850
       207F
             90 F2
                                                     *RECOVER MNEMONIC INDEX.
                                   PLA
0860
       2081
              48
                                   TAY
0870
       2082
             AR
                                   LDA MNEML,Y
                 79 21
0880
       2083
             В9
                                                     *FETCH 3-CHAR MNEMONIC
                                   STA LMNEM
             85 05
0890
       2086
                                                     (PACKED IN TWO BYTES)
                                   LDA MNEMR,Y
                    21
                В9
0900
       2088
             В9
              85 06
                                   STA RMNEM
0910
       208B
                           PRMN1
                                   LDA #$0
              A9 00
       208D
0920
              A0 05
                                   LDY #$5
0930
       208F
                           PRMN2
                                   ASL RMNEM
0940
       2091
              06 06
                                                     #SHIFT 5 BITS OF CHAR INTO 'A'.
0950
       2093
              26 05
                                   ROL LMNEM
                                                     # (CLEAR CARRY)
       2095
                                   ROL A
              2A
0960
                                   NEY
 0970
       2096
              88
                                   BNE PRMN2
       2097
              DO F8
 0980
                                   ADC #$3F
                                                     FADD '?' OFFSET.
 0990
       2099
              69
                 3E
                                                     FOUTPUT A CHAR OR MNEMONIC
       209B
              20 OB
                    21
                                   JSR OUTC
 1000
       209E
                                   DEX
 1010
                                   BNE PRMN1
 1020
        209F
              DO EC
                                   JSR PRBLNK
                                                     FOUTPUT 3 BLANKS
        20A1
              20 F1 20
 1030
                                                     COUNT FOR 6 PRINT FORMAT BITS.
              A2 06
E0 03
                                   LDX #$6
 1040
        20A4
                           PRADR1 CPX
                                       #$3
 1050
        20A6
                                                     FIF X=3 THEN PRINT ADDRESS VAL.
                                   BNE PRADR3
 1060
        20AB
              DO 12
                                   LDY LENGTH
 1070
        2044
              A4 04
                                                     :NO PRINT IF LENGTH=0.
                                   BEQ PRADR3
              FO OE
 1080
        20AC
                           PRADR2 LDA FORMAT
              45 03
 1090
        20AE
                                                     FHANDLE REL ADDRESSING MODE
                                   CMP #$E8
              C9 E8
 1100
        20B0
                                                     SPECIAL (PRINT TARGET ADDR)
                                   LDA (PCL),Y
              B1 00
 1110
        20B2
                                                     (NOT DISPLACEMENT)
                                   BCS RELADR
              BO 1C
 1120
        20B4
                                                     #OUTPUT 1- OR 2- BYTE ADDRESS.
                                    JSR PRBYT
 1130
        20B6
              20 13 21
                                                      *MORE SIGNIFICANT BYTE FIRST.
              88
                                    DEY
        20B9
 1140
                                    BNE PRADR2
              DO F2
```

1150

20BA

```
1160
      20BC
             06 03
                          PRADR3 ASL FORMAT
                                                    FTEST NEXT PRINT FORMAT BIT.
1170
      20BE
             90 OF
                                  BCC PRADR4
                                                    FIF O. DONT PRINT
1180
      20C0
             BD 6C 21
                                  LDA CHAR1-1.X
                                                    #CORRESPONDING CHAR.
1190
      20C3
             20 OB 21
                                  JSR OUTC
                                                    FOUTPUT 1 OR 2 CHARS
                                  LDA CHAR2-1.X
             BD 72 21
                                                    (IF CHAR FROM CHAR2 IS O.
1200
      20C6
             FO 03
                                                    DON'T PRINT IT)
                                  BEG PRADR4
1210
      2009
1220
      20CB
             20 OB 21
                                  JSR DUTC
                          PRADR4 DEX
1230
      20CE
             CA
1240
      20CF
             DO D5
                                  BNE PRADR1
                                                    RETURN IF DONE 6 FORMAT BITS.
1250
      20D1
             60
                                  RTS
                                                    *PCL,H + DISPL + 1 TO 'A','Y'.
             20 FF 20
1260
      20D2
                          RELADR JSR PCADJ3
1270
      20D5
             AA
                                  TAX
1280
      20B6
             E8
                                  INX
                                                    # +1 TO 'X','Y'.
1290
      20D7
             DO 01
                                  BNE PRNTYX
1300
      20D9
             C8
                                  INY
1310
      20DA
             98
                          PRNTYX TYA
                                                    PRINT TARGET ADDRESS OF BRANCH
                          PRNTAX JSR PRBYT
             20 13 21
1320
      20DB
                                                    #AND RETURN
1330
      20 DE
             RΔ
                          PRNTX
                                  TXA
                                      PRRYT
             4C 13 21
20 2F 1E
                                  JMP
1340
      20DF
                                                    FOUTPUT CARRIAGE RETURN.
      20F2
                          PRPC
                                  JSR CRLF
1350
                                  LDA PCH
      20E5
1360
             A5 01
                                  LDX PCL
1370
      20F7
             AA 00
                                  JSR PRNTAX
                                                    FOUTPUT PCL.+H
             20 DB 20
1380
      20E9
1390
      20FC
             A9 2D
                                  LDA #'-
                                  JSR OUTC
                                                    #OUTPUT '-'
             20 OB 21
      20FF
1400
                          PRBLNK LDX #$3
                                                    FBLANK COUNT
1410
      20F1
             A2 03
                          PRBL2
                                  LDA
1420
      20F3
             A9 20
                                  JSR OUTC
                                                    FOUTPUT A BLANK
             20 OB 21
                          PRBL3
1430
      20F5
                                  DEX
1440
      20F8
             CA
                                                    $LOOP UNTIL COUNT =0
             DO F8
                                  BNE PRBL2
1450
      20F9
                                  RTS
      20FB
1460
             60
                          PCADJ
                                  LDA LENGTH
                                                    #0=1-BYTE, 1=2-BYTE, 2=3-BYTE.
1470
      20FC
             A5 04
                          PCADJ2 SEC
1480
      20FE
             38
             A4 01
                          PCADJ3 LDY PCH
1490
      20FF
                                                    FTEST DISPL SIGN (FOR REL
1500
      2101
             AA
                                  TAX
1510
      2102
             10 01
                                  BPL PCADJ4
                                                    FBRANCH). EXTEND NEG
                                                    #BY DECREMENTING PCH.
1520
      2104
             88
                                  DEY
1530
      2105
             65 00
                          PCADJ4 ADC PCL
                                  BCC RTS1
                                                    #PCL+LENGTH (OR DISPL) +1 TO 'A'.
#CARRY INTO 'Y' (PCH)
1540
      2107
             90 01
      2109
             C8
1550
                                  INY
                          RTS1
1560
      210A
             60
                                  RTS
             84 07
                                       YSAVE
1561
      210B
                          OUTC
                                  STY
1562
      210D
             20 A0 1E
                                  JSR OUTCH
1563
             A4 07
                                  LDY
                                       YSAVE
      2110
1564
      2112
             60
                                  RTS
1565
      2113
             84 07
                          PRBYT
                                  STY
                                      YSAVE
1566
             20 3B 1E
                                  JSR PRIBYT
      2115
             A4 07
                                  LDY
                                       YSAVE
1567
      2118
1568
      211A
             60
                                  RTS
1570
      211B
1580
      211B
1590
      2118
                           THE TABLES FOLLOW---
1600
      211B
1610
                          MODE
                                  .BYTE $40,$2,$45,$3,$D0,$8,$40,$9,$30
      211B
1610
      211C
             02
1610
      211D
             45
1610
      211E
1610
      211F
             DO
1610
      2120
             08
1610
      2121
             40
1610
      2122
             09
1610
      2123
             30
1620
      2124
                           :XXXXXXZO INSTRUCTIONS.
             22
                                  .BYTE $22,845,$33,$D0,$8,$40,$9,$40,$2,$45
1630
      2124
1630
      2125
             45
1630
      2126
             33
      2127
1630
             DO
1630
      2128
             08
             40
1630
      2129
1630
      212A
1630
      212B
             40
1630
      2120
             02
1630
      212D
             45
                           ;Z=O, LEFT HALF BYTE
1640
      212E
                           Z=1, RIGHT HALF BYTE
1650
      212E
                                  .BYTE $33,$D0,$8,$40,$9,$40,$2,$45,$B3,$D0
1660
      212E
1660
      212F
             DO
      2130
1660
             08
1660
      2131
             40
1660
      2132
1660
      2133
             40
1660
      2134
             02
1660
      2135
             45
             В3
1660
      2136
1660
      2137
             D()
1670
      2138
             08
                                  .BYTE $8,$40,$9,$0,$22,$44,$33,$D0,$80,$44
1670
      2139
             40
1670
      213A
             09
1670
      213B
             00
1670
      213C
             22
1670
      213D
             44
1670
             33
      213E
```

page 6

1670

1670

1670

213F

2140

2141

DO

80

44

```
1680
       2142
             00
                                  .BYTE $0,$11,$22,$44,$33,$D0,$8C,$44,$9A,$10
1680
       2143
             11
1680
       2144
1680
       2145
             44
1680
       2146
             33
1680
       2147
             DO
1680
       2148
             80
1680
       2149
             44
1680
       214A
             9A
1680
       214B
             10
1690
       214C
             22
                                  .BYTE $22,$44,$33,$B0,$8,$40,$9,$10,$22,$44
1690
       214D
             44
1690
       214E
             33
1690
       214F
             DO
1690
       2150
             08
1690
       2151
1690
       2152
             09
             10
1690
       2153
1690
       2154
             22
1690
       2155
             44
1700
       2156
             33
                                  .BYTE $33,$B0,$8,$40,$9,$62
1700
       2157
             DΩ
1700
       2158
             OΒ
1700
       2159
             40
1700
      215A
             0.6
1700
      215B
             62
1710
      215C
                          FYYXXXZ01 INSTRUCTIONS
1720
      2150
             13
                                  .BYTE $13,$78,$A9
1720
      215D
             78
1720
1730
      215E
215F
             49
             00
                          MODE2 .BYTE $0
                                                    FERR
1740
                                  .BYTE $21
.BYTE $01
      2160
             21
                                                    FIMM
1750
      2161
             01
                                                    #Z-PAG
1760
                                  .BYTE $02
      2162
             02
                                                    FABS
1770
      2163
             00
                                  .BYTE $0
                                                    FIMPL
1780
      2164
             80
                                  .BYTE $80
.BYTE $59
                                                    FACC
1790
      2165
             59
                                                    F(Z-PAG,X)
                                  .BYTE $4D
.BYTE $11
1800
      2166
             4D
                                                    (Z-PAG),Y
1810
                                                    FZ-PAG.X
      2167
             11
                                  .BYTE $12
1820
      2168
             12
                                                    ABS . X
                                  BYTE $6
1830
      2169
             06
                                                    FABS . Y
                                  .BYTE $4A
.BYTE $5
1840
      216A
             4A
                                                    (ABS)
1850
      216B
             05
                                                    FZ-PAG . Y
                                1860
      216C
             10
1870
      216D
                          CHAR1
1870
      216E
             29
1870
      216F
             20
1870
      2170
             23
      2171
2172
1870
             28
1870
             41
      2173
             59
1890
                          CHAR2 .BYTE $59,$0,$58,$00,$0,$0
1890
      2174
             00
      2175
1890
             58
1890
      2176
             00
1890
      2177
             00
1890
      2178
             00
1900
      2179
                          $XXXXX000 INSTRUCTIONS
1910
      2179
             1 C
                          MNEML .BYTE $10,$8A,$10,$23,$5D,$8B,$1B,$A1,$9D
1910
      217A
             8A
1910
      217B
             10
1910
      217C
             23
1910
      217D
             5D
1910
      217E
1910
      217F
             1 B
1910
      2180
1910
      2181
             91
1920
      2182
             88
                                  .BYTE $8A,$1D,$23,$9D,$8B,$1D,$A1,$0,$29,$19
1920
      2183
             1 D
1920
      2184
             23
1920
      2185
             9D
1920
      2186
             8B
1920
      2187
             1 D
1920
      2188
             A1
1920
      2189
             00
1920
      218A
             29
1920
      218B
             19
1930
      218C
             ΑE
                                  .BYTE $AE,$69,$AB,$19,$23,$24,$53,$1B,$23
1930
      218D
             69
1930
      218F
             AB
1930
      218F
             19
1930
      2190
             23
1930
      2191
             24
1930
      2192
             53
      2193
1930
             18
1930
      2194
             23
1940
      2195
             24
                                  .BYTE $24,$53,$19,$A1,$0
1940
      2196
             53
1940
      2197
             19
1940
      2198
             A1
1940
      2199
             00
```

```
1950
      219A
                          $XXXYY100 INSTRUCTIONS.
      219A
                                  .BYTE $1A,$5B,$5B,$A5,$69,$24,$24
1960
1960
      219B
             5B
1960
      219C
             5B
1960
      219D
1960
      219E
             69
1960
      219F
1960
      21A0
             24
1962
      21A1
                          #1XXX1010 INSTRUCTIONS
1963
      21A1
             ΑE
                                  .BYTE $AE,$AE,$AB,$AD,$29,$0,$70,$0
1963
      21A2
             AE
1963
      21A3
1963
      21A4
             ΑD
1963
      21A5
1963
      21A6
1963
      21A7
1963
      21A8
             00
1964
      21A9
                          #XXXYYY10 INSTRUCTIONS
1965
      21A9
             15
                                  .BYTE $15,$9C,$6D,$9C,$A5,$69,$29,$53
1965
      21AA
             9C
1965
      21AB
             6D
      21AC
21AD
1965
             90
1945
             Δ5
1965
      21AE
             49
1965
      21AF
             29
1965
      21B0
             53
                          *XXXYY01 INSTRUCTIONS.
1970
      21B1
1980
                                  .RYTE $84.$13.$34.$11.$45.$69.$23.$40
      21B1
             84
1980
      21B2
             13
1980
      21B3
             34
      2184
1980
             11
1980
      2185
             Α5
1980
      21B6
             69
1980
      21B7
             23
      2188
1980
             A0
1990
      21B9
                          ;XXXXX000 INSTRUCTIONS.
2000
      21B9
             D8
                          MNEMR .RYTE $D8, $62, $5A, $48, $26, $62, $94, $88
2000
      21BA
2000
      21BB
2000
      21BC
             48
2000
      21BD
             26
2000
      21BE
             62
2000
      21BF
2000
      21C0
             88
2010
      2101
             54
                                  .BYTE $54,$44,$CB,$54,$68,$44,$E8,$94,$0,$B4
2010
      21C2
             44
2010
      21C3
             CB
2010
      2104
             54
2010
      2105
             68
2010
      21C6
             44
2010
      21C7
             E8
2010
      2108
             94
      2109
             00
2010
2010
      21CA
             B4
                                  .BYTE $8,$84,$74,$B4,$28,$6E,$74,$F4,$CC,$4A
      21CB
2020
             OB
      2100
2020
             84
2020
      2100
             74
2020
      21CE
             B4
2020
      21CF
             28
2020
      21D0
             6E
2020
      2101
             74
2020
      21D2
             F4
2020
      2103
             CC
2020
      21D4
             44
2030
      2105
                                  .BYTE $72,$F2,$A4,$8A
2030
      21D6
2030
      21D7
2030
      21D8
             BA
                          $XXXYY100 INSTRUCTIONS.
2040
      21D9
2050
      21D9
             00
                                  .BYTE $0,$AA,$A2,$A2,$74,$74,$74,$72
2050
      21 DA
             AA
2050
      21DB
             42
2050
      21DC
             A2
2050
             74
      2100
2050
             74
      21DE
2050
      21DF
             74
2050
      21E0
             72
                          $1XXX1010 INSTRUCTIONS.
2060
      21E1
                                  .BYTE $44,$68,$82,$32,$82,$0,$22,$0
2070
      21E1
             44
2070
      21E2
             68
2070
      21E3
             B2
2070
      21E4
             32
2070
      21E5
             B2
2070
      21E6
             00
2070
      21E7
2070
      21E8
             00
2080
      21E9
                          ;XXXYYY10 INSTRUCTIONS.
                                  .BYTE $1A,$1A,$26,$26,$72,$72,$88,$C8
2090
      21E9
             1 A
2090
      21EA
             1A
2090
      21EB
             26
2090
      21EC
             26
```

2090

2090

2090

2090

21ED

21EE

21EF

21F0

72

88

C8

2100	21F1		<pre>;XXXYYY01 INSTRUCTIONS</pre>
2110	21F1	C4	BYTE \$C4, \$CA, \$26, \$48, \$44, \$44, \$A2, \$CB
2110	21F2	CA	
~ 4 4 ^	04-	~ .	

2110 21F4 48 2110 21F5 44 2110 21F6 44 2110 21F7 A2

21F8

21F9

CB

2110

2120

FINISH .END

CHECK-OUT

by Robert D. Larrabee 18801 Woodway Drive Derwood, MD 20855

Did you ever want to check-out a new program without having to continually hit the plus key of your KIM? Did you ever wish you could back-up a byte or two? Did you ever want to add some material in the middle of a program without having to reenter all of the succeeding bytes? If you ever did, program CHECK-OUT is for you!

Load this program into the stack page, push the PC key to enter the starting address (0100), and then push the GO key. The display will show address 0000 and the contents of that memory location. Then push the B key to start automatically scanning through memory twoard the Back of the program, or the F key to start scanning toward the $\underline{\underline{F}}$ ront of the program. The keys 1 through 9 control the scan speed. The zero key stops the scan at the displayed address. The A key stops the scan one position beyond the currently displayed address, while the E key stops the scan one position previous to the currently displayed address. If the scan speed is set to 9 (the fastest possible), the A and E keys are equivalent to an immediate one step forward or backward. Because the plus key was there, it was given its normal function.

If, in scanning a program, an error is found, stop the scan at the error (by pushing the zero key at the error, or stepping there with the A, E, or plus keys). The push the DA key, and you will enter the KIM monitor in data mode. The corrected data can then be immediately entered from the keyboard, and you can then return to program CHECK-OUT by pushing the ST key.

If you wish to make a large jump in address, and scanning there at speed 9 would take too long, push the AD key to enter the KIM monitor in address mode. The new address of interest can then be immediately entered from the keyboard, and you can then return to program CHECK-OUT by pushing the ST

0116 A2 01

0118 8E FB 17

The C key Creates spaces for additional bytes in a program by moving the program material down from the displayed address one unit each time the C key is depressed. The byte displayed and all following bytes are moved down and the created space at the displayed address is filled with zeros. The D key Deletes the displayed byte by moving up all the following program material one unit each time the D key is depressed. Neither the C or D key effects the portion of the program before the displayed address. The table below shows what address program CHECK-OUT considers to be the end of the program. Notice that this depends on the page currently being displayed when the C or D key is depressed. If desired, these ending locations can be changed by entering appropriate new address in-formation at the locations indicated in the last two columns of the table.

When attempting to do something program CHECK-OUT considers illegal (for example, modifying some of its own instructions on page 1), the display will go blank for as long as the illegal key is depressed, and then all will return to the previous conditions when the illegal key is released.

Program CHECK-OUT does nothing in the way of changing branch instruction addresses when creating or deleting spaces. If this feature is desired, I invite you to write a routine to perform this address manipulation. Change the branch instruction at location OlD1 in program CHECK-OUT to branch to your routine, and then return to address 0104 in program CHECK-OUT at the end of your routine.

	Page of current	Address taken as the end of		these data am CHECK-OUT
	address	the program	High	Low
	0 1	OOEE not allowed	-	0187
i	2-16	O3FF	0193	0195
	17	17E6	- i	0199
	above 17	not allowed	-	

STORAGE AREA

LDX #01

STX 17FB

00EF 00 00F0 01 00F1 00 00F2 FF 00F3 00 00F4 00 00F5 05 00F6 00 00F7 00 00F8 FF 00F9 00 00FA FA 00FB 00 00FC 01 00FD 00 00FF 00		PCL PCH PREG SPUSER ADH SS RD MODE LC INH POINTL POINTH TEMP1 TEMP2	program counter, low program counter, high status register stack pointer current address, low current address, high scan speed (0-9) read disable (disable if not zero) mode of operation (stop scan if ze loop counter for display loop data position for display pointer address, low pointer address, high temporary storage register #1 temporary storage register #2 not used not used	
		MAIN PRO	OGRAM STARTS HERE	CPU is in The
0100 A9 00 0102 85 FB 0104 A5 FA 0106 85 F3 0108 A5 FB 010A 85 F4 010C A2 FF 010E 9A 010F 86 F8 0111 A2 04 0113 8E FA 17	ENTRY START	LDA #00 STA POINTH LDA POINTL STA ADL LDA POINTH STA ADH LDX #FF TXS STX LC LDX #04 STX 17FA	initial entry into program set initial value of POINTL get pointer address, low store pointer address, low in ADL get pointer address, high in ADH initial value of SPUSER and LC initialize stack pointer to #FF initialize loop counter to #FF value for interrupt vector, low initialize interrupt vector, low initialize interrupt vector, low	\$ 00F1 = \$00

value for interrupt vector, high


initialize interrupt vector, high

SYM-1, 6502-BASED MICROCOMPUTER

- FULLY-ASSEMBLED AND COMPLETELY INTEGRATED SYSTEM that's ready-to-use
- . ALL LSI IC'S ARE IN SOCKETS
- 28 DOUBLE-FUNCTION KEYPAD INCLUDING UP TO 24 "SPECIAL" FUNCTIONS
- . EASY-TO-VIEW 6-DIGIT HEX LED DISPLAY
- KIM-1* HARDWARE COMPATIBILITY

The powerful 6502 8-Bit MICROPROCESSOR whose advanced architectural features have made it one of the largest selling "micras" on the market today.

- THREE ON-BOARD PROGRAMMABLE INTERVAL TIMERS available to the user, expandable to five on-board.
- 4K BYTE ROM RESIDENT MONITOR and Operating Programs.
- · Single 5 Volt pawer supply is all that is required
- 1K BYTES OF 2114 STATIC RAM anboard with sockets provided for immediate expansion to 4K bytes onboard, with total memory expansion to 65, 536 bytes.
- USER PROM/ROM: The system is equipped with 3 PROM/ROM expansion sockets far 2316/2332 ROMs or 2716 EPROMs
- ENHANCED SOFTWARE with simplified user interface
- . STANDARD INTERFACES INCLUDE:
 - —Audio Cassette Recorder Interface with Remote Cantrol (Two modes: 135 Baud KIM-1* compatible, Hi-Speed 1500 Baud)
 - -Full duplex 20mA Teletype Interface
 - -System Expansion Bus Interface
 - -TV Cantroller Board Interface
 - -CRT Compatible Interface (RS-232)
- APPLICATION PORT: 15 Bi-directional TTL Lines for user applications with expansion capability for added lines
- EXPANSION PORT FOR ADD-ON MODULES (51 I/O Lines included in the basic system)
- SEPARATE POWER SUPPLY cannector for easy disconnect of the d-c power
- AUDIBLE RESPONSE KEYPAD



Synertek has enhanced KIM-1* software as well as the hardware. The software has simplified the user interface. The basic SYM-1 system is programmed in machine language. Monitar status is easily accessible, and the monitor gives the keypad user the same full functional capability of the TTY user. The SYM-1 has everything the KIM-1* has to after, plus so much more that we cannot begin to tell you here. So, if you want to know more, the SYM-1 User Manual is available, separately.

SYM-1 Complete w/manuals \$269.00 SYM-1 User Manual Only 7.00

SYM-1 Expansion Kit 75.00Expansion includes 3K of 2114 RAM chips and 1-6522 I/O chip.

SYM-1 Manuals: The well organized documentation package is complete and easy-to-understand.

SYM-1 CAN GROW AS YOU GROW. Its the system to BUILD-ON. Expansion features that are soon to be offered:

*BAS-1 8K Basic ROM (Microsoft)

\$159.00

*KTM-2 TV Interface Board

349.00

*We do honor Synertek discount coupons

QUALITY EXPANSION BOARDS DESIGNED SPECIFICALLY FOR KIM-1, SYM-1 & AIM 65

These boards are set up far use with a regulated power supply such as the one below, but, provisions have been made so that you can add onboard regulators for use with an unregulated power supply. But, because af unreliability, we do not recommend the use of onboard regulators. All 1.C.'s are socketed for ease af maintenance. All boards carry full 90-day warranty.

All products that we manufacture are designed to meet or exceed industrial standards. All components are first quality and meet full manufacturer's specifications. All this and an extended burn-in is done to reduce the normal percentage of field failures by up to 75%. To yau, this means the chance of inconvenience and lost time due to a failure is very rare; but, if it should happen, we guarantee a turn-around time of less than forty-eight hours for repair.

Our money back guarantee: If, for any reason you wish to return any board that you have purchased directly from us within ten (10) days after receipt, complete, in original condition, and in ariginal shipping carton; we will give you a complete credit ar refund less a \$10.00 restocking charge per board.

VAK-1 8-SLOT MOTHERBOARD

This motherboard uses the KIM-4* bus structure. It provides eight (8) expansion board sockets with rigid card cage. Separate jacks for audio cassette, TTY and power supply are provided. Fully buffered bus.

VAK-1 Motherboard

\$129.0

VAK-2/4 16K STATIC RAM BOARD

This board using 2114 RAMs is configured in two (2) separately addressable 8K blocks with individual write-protect switches.

VAK-2 16K RAM Board with only 8K of RAM (½ populated) VAK-3 Complete set of chips to \$239.00

expand above board to 16K
VAK-4 Fully populated 16K RAM

\$175.00

\$379.00

VAK-5 2708 EPROM PROGRAMMER

This board requires a +5 VDC and +12 VDC, but has a DC to DC

multiplyer so there is no need far an additional power supply. All software is resident in on-board ROM, and has a zero-insertion socket.

VAK-5 2708 EPROM Programmer

\$269.00

VAK-6 EPROM BOARD

This board will hold 8K af 2708 or 2758, or 16K of 2716 or 2516 EPROMs. EPROMs not included.

VAK-6 EPROM Board

\$129.00

VAK-7 COMPLETE FLOPPY-DISK SYSTEM (May '79)

VAK-8 PROTYPING BOARD

This board allows you to create your own interfaces to plug into the motherboard. Etched circuitry is provided for regulators, address and data bus drivers; with a large area for either wire-wrapped or soldered IC circuitry.

VAK-8 Protyping Board

\$49.00

POWER SUPPLIES

ALL POWER SUPPLIES are totally enclosed with grounded enclosures for safety, AC power cord, and carry a full 2-year warranty.

FULL SYSTEM POWER SUPPLY

This power supply will handle a microcomputer and up to 65K of our VAK-4 RAM. ADDITIONAL FEATURES ARE: Over voltage Protection on 5 volts, fused, AC on/off switch. Equivalent to units selling for \$225.00 or more.

Provides +5 VDC @ 10 Amps & ±12 VDC @ 1 Amp VAK-EPS Power Supply \$

\$125.00

KIM-1* Custom P.S. provides 5 VDC @ 1.2 Amps and +12 VDC @ .1 Amps KCP-1 Power Supply

SYM-1 Custom P.S. provides 5 VDC @ 1.4 Amps

\$41.50

VCP-1 Power Supply

\$41.50



2967 W. Fairmount Avenue Phoenix AZ. 85017 (602)265-7564





DISPLAY/KEYBOARD-DECODE LOOP

011B A9 011D 8D 0120 20 0123 D0 0125 85 0127 F0 0129 A5 012B D0 012D E6 012F 20 0134 F0 0136 AA 0137 38 0138 E9 013A 10 013C 49 013E 85 0140 10	0 47 1 0 19 1 0 04 6 F6 9 43 8 F6 9 6A 1 00 32 0A 06 FF F5	F AGAIN ONE	LDA #80 STA 1747 JSR SCAND BNE ONE STA RD BEQ DONE LDA RD BNE DONE JOR GETKEY CMP #00 BEQ MZERO TAX SEC SBC #0A BPL TWO EOR #FF STA SS BPL DONE	value to store in the timer start timer activate display branch if any key is depressed enable the reading of the keyboard unconditional branch to end of loop get value of read disable branch to end of loop if RD not zero set read disable to #01 read keyboard is the zero key depressed? branch if the zero key is depressed store keycode in X register required by next instruction subtract #0A from keycode branch if keycode is not speed control compute new value of speed store new value of speed in SS unconditional branch to end of loop
0142 8A 0143 C9 0145 F0 0147 10 0149 C9 014B D0 014D 4C 0150 29 0152 C9 0154 F0 0156 A4 0158 88 0159 F0 015B A5 015D F0	36 23 10 03 7C 1C 0A 0A 14 FB	TWO KIM THREE	TXA CMP #12 BEQ PLUS BPL DONE CMP #10 BNE THREE JMP 1C7C AND #0A CMP #0A BEQ MODE LDY POINTH DEY BEQ ERROR LDA MODE BEQ FOUR BPL ERROR	return keycode to accumulator is the plus key depressed? branch if plus key depressed ignore unused keys is the AD key depressed? branch if AD key not depressed enter the KIM monitor result not #0A for C, D, & DA keys result is #0A for A, B, E, & F keys branch if key is A, B, E, or F load page number into Y register decrement page number in Y register blank display if page number = 1 load mode into Y register branch if mode is zero
0161 8A 0162 C9 0164 F0 0166 D0 0168 A2 016A 86 016C AD 0175 C5 0177 90 0175 C5 0177 90 017B F0 017B R0 017B A6	11 E7 1C 00 F7 47 17 AF F8 F8 F8 F5 A2 F7 04	MZERO MODE DONE	TXA CMP #11 BEQ KIM BNE MOVE LDX #00 STX MODE LDA 1747 BEQ AGAIN INC LC LDA LC CMP SS BCC LOOP1 LDX MODE BEQ FIVE TXA JSR NEXT JMP START	blank display if mode not zero return keycode to accumulator is the DA key depressed? enter the KIM monitor if DA key branch if C or D key depressed the new value of mode store the new value of mode test the clock display again if not time add one to loop counter get new value of loop counter compare to total number desired do another loop if necessary get value of mode return to START if mode is zero put mode in accumulator set up next POINTL and POINTH end of display/keyboard loop

ROUTINE TO SERVICE THE C AND D KEYS

0184 86 FC 0186 A0 EE 0188 A5 F4 018A F0 0E 018C C9 17 018E B0 9D 0190 B0 9D 0192 A9 03 0194 A0 FF 0196 30 02 0198 A0 E6 019A 84 FA 019C 85 FB 019E A0 00 01A0 B1 FA 01A2 AA 01A3 98 01A4 91 FA 01A6 20 EE 01 01A9 A5 FC 01AB C9 0D 01AD F0 0B 01AF B1 FA 01B1 C8 01B2 91 FA 01B1 C8 01B2 91 FA 01B6 88 01B5 98 01B6 91 FA 01BC 85 FD 01BA B1 FA 01BC 85 FD 01BB 8A 01BC 85 FD 01BB 8A 01BC 85 FD 01BC 85 FD 01BC 85 FD 01CT A6 FD 01CT A6 FD 01CT A6 FD	SIX SEVEN LOOP2 CKEY TEST	STX TEMP1 LDY #EE LDA AOH BEQ SEVEN CMP #17 BEQ SIX BCS ERROR LDA #03 LDY #FF BMI SEVEN LDY #E6 STY POINTL STA POINTL, Y JSR SUB LDA TEMP1 CMP #0D BEQ DKEY LDA POINTL, Y INY STA POINTL, Y INY STA POINTL, Y BEQ TEST LDA POINTL, Y STA TEMP2 TXA STA POINTL, Y LDA ADH CMP POINTH	store keycode in TEMP1 location of useful end of page zero put page number in accumulator branch if page zero is page number equal to 17? branch if page number is 17 blank display if page number > 17 end page in unexpanded KIM system RAM location of end of page unconditional jump location of useful end of page 17 store end of page location in POINTL store end page number in POINTH value needed for (indirect), Y addressing LDA with byte at the end of the last page store byte in the X register bring #00 to accumulator put zero in end of page location decrement POINTL/POINTH get keycode from TEMP1 which key (C or D) is depressed? branch if D key is depressed get byte at pointed location increment Y register to unity store byte in next larger address decrement Y register to zero set accumulator to zero set accumulator to zero store zero in pointed location branch around D key instructions get byte at pointed location store temporarily in TEMP2 bring following byte to accumulator store byte in pointed location retrieve stored byte ADH is endpoint of POINTH has final page been reached?
01C9 D0 06		BCC LOOP2 BNE END	if not, loop back all done if ADH > POINTH

01CB A5 F3 01CD C5 FA 01CF 90 D5 01D1 4C 04 01 END 01D4 EA	LDA ADL CMP POINTL BCC LOOP2 JMP START NOP	ADL is endpoint of POINTL has final location been reached? if not, loop back end of C and D key routine not used
01D5 EA	NOP	not used

SUBROUTINE TO STEP POINTL AND POINTH

01D6 01D8 01DC 01DE 01DF 01E0 01E2 01E4 01E5 01E7 01EB 01ED 01FC	29 D0 84 88 8A 29 D0 8C 5C 6C 6C A9	01 02 F7 04 0A FA 02 FB FA	NEXT EIGHT ADD NINE SUB	AND BNE STY DEY TXA AND BNE TYA CMP BNE INC INC RTS DEC LDA	#04 SUB POINTL NINE POINTH POINTL POINTL	possible new value of mode is least significant digit zero? F and B keys require nonzero mode A and E keys require zero mode decrement Y register to #FF bring mode to accumulator in which direction is the scan? branch if E or F key depressed bring #FF to accumulator is POINTL equal to #FF? branch if not equal to #FF increment POINTL to new value return decrement POINTL to new value needed for next instruction is POINTL equal to #FF?
OTEE	C6		SUB	DEC		decrement POINTL to new value
01F0 01F2 01F4 01F6 01F8	C5 D0 C6	FA 02	RETURN	CMP BNE	#FF POINTL RETURN POINTH	needed for next instruction is POINTL equal to #FF? branch if not equal to #FF decrement POINTH to new value return

RESERVED FOR STACK

01F9 to 01FF

LANGUAGE LAB basic

BASIC MOD & PROGRAMMING HINT

by Heinz Joachim Schilling, DJ1XK Im Grun 15 D-7750 Konstanz 16 W Germany

Two days ago my copy of 6502 User Notes arrived, and because of new format and content I must say: Congratulations !!! You have arranged it into several sections, so it is quite easy to find an object of special personal interest. In my case it is BASIC.

You rised a BASIC question, and I have the solution. The problem of re-loading programs comes from a programming error of the Microsoft people. They did not realize that

1. the ID = \$00 or \$FF are only operable

- . the ID = \$00 or \$FF are only operable if the tape was not saved with an ID of \$00 or \$FF.
- loading to a changed address using \$FF in \$17F9 is not possible with their tapes as they use \$FF in \$17F9 during save!

You have to change the LDA \$FF into LDA \$FE at \$274, the \$FE is at \$2744, and that's all! You should have a look into the listing of the KIM-loader to see that ID=\$FF only comes into operation after the compare between the \$17F9-ID and the tape-ID, in our case the compare matches and the tape is loaded to the same location as it is saved.

You are right that the BREAK-Test should include the 30 as an opcode. $% \begin{center} \begin{$

The KIM BASIC hint regarding inputting only a 'return' is good, and I have another one!

In every case you try to use the cursor control codes in PRINT-statements with a semi-colon at the end you run into trouble: after 72 chars (or any other number you inputted at the cold start) the BASIC thinks the line would be complete you inserts a CR-LF, and off you are. This is true in all sorts of games (3 cushion billiard, life and so on). But the solution is so easy: add a simple POFF and overwthing will run.

a simple POKE, and everything will run:
1000 PRINT CHR\$(9);:POKE 22,1:REM CURSOR RIGHT
The POKE goes to the memory cell which holds the
position in the line. The storage of the 1 let

the BASIC think it was at the beginning of the line and so the inclusion of the unwanted CR-LF is dropped.

Besides, I have made a little program with subroutines of HYPERTAPE and LOAD in the same form as they are used in the Micro Ade Assembler, that means with optical control of the loading. can see on the 7-segment-display three different states: SYNC, Loading and seeking (that means if your load was with a fault and the loader looks for another ID). This little program has routines for calling these subroutines, and it can start BASIC and can start other programs at a specific address. I use the loader and save-subs from BASIC too, and so my BASIC is in the memory in 3 minutes instead of 18! Besides, I have made a disassembler printout of BASIC to allow easier corrections to BASIC. I think it would be possible to PROM the BASIC with trig functions, but this would be only possible in 9K, and you would have to change something in the coldstart routine. You must only make a little correction to the "Want SIN..." routine and take the first address after the PROM as beginning of free memory to \$78, \$79, e.g. the Want Sin prompting will be deleted.

The renumbering program on page 12 seems to be good, but I want to make one in assembler which could be loaded to my spare memory at \$0400 and must not be deleted at the end of the operation.

I just remember another little correction to my BASIC: I changed the location \$243A to \$E5 which allows the use of the DEL key at my terminal instead of the underline to delete a wrong character.

The most important thing during work with BASIC for nay corrections: a disassembler print-out!!!!

Then it is very easy to follow the flow through the interpreter and make little changes.

BASIC OUTPUT PAGING MOD

by Dick Grabowsky HDE, Inc. Box 120 Allamuchy NJ 07820

Marvin Dejong asks where to look to make Basic list 16 lines, rather than scoot the program past his eyes so quickly he can't see it.

Microsoft Basic does not use the KIM CRLF routine. Rather, it outputs a CR (OD) and line feed (OA) followed by a number of nulls as defined

page 12

in LOC \$15. These characters are all transfered to the KIM OUTCH routine. In 9-digit Microsoft Basic, the call to KIM OUTCH is located at \$2A51. To limit output, we can intercept this call, count the number of times the CR or LF character pass through our intercept, then halt further output until the operator inputs some character from the kevboard.

The following routine does this by counting the line-feed characters and stopping output until a line-feed is entered via the keyboard. As a bonus, let's add an ability to stop output (i.e. terminate the process) when we've found what we want, or have seen enough. The routine maybe placed anywhere in memory that will not be overwritten by Basic or Basic programs/data.

LINCHT	CMP #\$OA	; is it a line feed?
	BNE LINC1	;no, then output
	INC COUNTR	;yes, incr the counter
	LDA COUNTR	; and check to see if
	CMP LNCNT	;it ='s preset line count
	BEQ LINC2	;yes, -halt output
	LDA #\$OA	;else, reload line feed
LINCI	JMP \$1EA0	; (KIM OUTCH)
LINC2	LDA #0	
	STA COUNTR	reset the counter;
LINC3	JSR \$1E5A	;(KIM GETCH) get a char
	CMP #\$OA	;line feed?
	BEQ LINC1	yes, continue listing;
	CMP #\$OD	
	BNE LINC3	, ,
	JMP \$0	else, jump to "warm start"

COUNTR *=*=1 :line feed counter *=*=1 LNCNT :line count

To use the routine, set the address of "LINCNT" at \$2A52, \$2A53. Preset the values of "COUNTR" to zero and "LNCNT" to the desired number of lines (use HEX). All output will then be limited to the number of lines defined by LNCNT. Since Basic does not use zero page locations from \$DD up, \$DD and \$DE may be good locations to put "COUNTR" and "LNCNT" since this can be done before loading Basic from tape.

When in Basic, the routine can be used to limit output to a specific number of lines by "poke" ing the values of "COUNTR" and "LNCNT" as appropriate،

One additional note, 9 digit Basic sets the base address for programs at locations \$4148 and \$414A to 41 and 40, respectively. To gain room above Basic for additional software, changing these locations to the address values desired will do the trick. By the way, to check on the authors of Microsoft Basic, enter an "A" in response to the "memory size?" question.

> 0010: 0010:

0212:

0213:

0220:

RENUMBER ADDENDUM AND SOME MODS

by Harvey Herman Dept. of Chemistry Univ. of North Carolina Greensboro, NC 27412

I recently sent you a BASIC renumbering program for KIM Microsoft 8K BASIC. In the accompanying letter I noted one restriction about the number of digits in the new line number. Sean McKenna has written me about one further restriction.
He notes that numbers after THEN in an assignment, for example, will always be renumbered. Thus, the 2 in 10 IF A = 1 THEN X=2 could be inadvertently changed. He suggests using variables in assignments after THEN (X = V, where V = 2) to avoid the problem.

I also mentioned another renumbering program I use which utilizes a paper tape punch. This program does not have the above problem. If readers are interested in this program I will send it to them on receipt of a SASE and extra loose stamp.

I wrote you recently about the question you posed to your readers about Microsoft BASIC. It is possible to automate the "Y" answer in an initialization routine and I documented the procedure. A further point-4146 can be changed to 4E or 41 if "N" or "A" is the desired response.

In reply to a question posed to me in a private letter I have figured out how to skip all 3 initialization questions and their accompaning messages.

1.	To size memo	ry auto	matica	11v	change-	•
	Locations	From	Τo			,
	4089	20	4 C	JMP	\$40CD	
	40BA	18	CD			
	40BB	2 A	40			

2 .	To keep 7	2 as	termina	al wid	dth	
	410A		20	4 C	JMP	\$4136
	410B		18	36		
	410C		2 A	41		

3.	To answer "Y" skip message	to	trig f	unctio	ns quest	ion and
	413A	20	4C	JMP	\$4145	
	413B	18	45			
	413C	2 A	41			
-	4145	CO	A 9	LDA	#'Y or	'N or 'A
	4146	00	59	or 4E	or 41	

AUTOMATIC LINE NUMBER ENTRY PROMPT FOR BASIC Sean McKenna

0010:	sean mckenna
0020:	64 Fairview Ave.
0030:	Piedmont, CA 94610
0040:	January, 1979
0050:	•
0060:	
0061:	NUMBER REVISED VERSION
0062:	
0070:	An automatic line numbering input routine
0080:	for 9 digit KIN EASIC. From command BASIC
0090:	enter # nnnn+ii(sp)CR to begin automatic
0100:	line number sequencing with nnnn. Each
0110:	line will be incremented by ii. To return
0120:	to command BASIC enter CR after line number.
0130:	On delete the line number will be repeated
J140:	on the next line of the terminal. Don't
0150:	
	forget the space after the increment number
0160:	or you may get no increment at all or a
0170:	strange one. Because of the decimal add
0180:	the highest line number possible with the
0190:	program is 9999 and 99 is the highest
0200:	increment
3210:	
0211:	Initialization: SEQFLG and WIMNUM must be

initialized to \$00 before using the routine

```
0230: 0200
                      NUMBER ORG
                                    $0200
0240: 0200
                      INCR
                                    S00E5
                      SEQFLG
0250: 0200
                                    S00E6
0260: 0200
0270: 0200
                      TIMNUM *
                                    $00E7
                                    $00E8
                      ΗI
0280: 0200
                                    $00E9
                      LO
0290: 0200
                      BASBUF
                                    $001B
                      PACKT
                                    S1A00
0300: 0200
                      SAVX
0310: 0200
                                    $17E9
0320:
                       Set input and output to your routines.
                       Input should echo to output and preserve X.
0330:
                      Output should preserve X and ACC.
INPUT * $1000
0340:
0350: 0200
                      OUTPUT *
0360: 0200
                                    $1017
0370:
0380:
                        Enter here from KIM BASIC INPUT call
                                    TIMNUM If not time to output a line number
0390: 0200 24 E7
                      START BIT
0400: 0202 10 14
                             BPI.
                                    TNP
                                           Then branch to input call
0410: 0204 A5 E8
                      LINO
                             LDA
                                    нт
                                           Otherwise output a 4 digit line number to
                                    OUTNUM the BASIC input buffer and users display
0420: 0206 20 6A 02
                             JSR
0430: 0209 A5 E9
                             LDA
                                    LO
0440: 020B 20 6A
                              JSR
                                    OUTNUM
                              LDAIM $00
                                           and clear the TIMNUM flag
0450: 020E A9 00
0460: 0210 85 E7
                              STAZ TIMNUM
                                    $20
0470: 0212 A9 20
                             LDAIM
                                           Output a space
0480: 0214 20 17 10
                             JSR
                                    OUTPUT
0490: 0217 60
                             RTS
                                           and return to basic
0500: 0218 20 00
                  10
                      INP
                              JSR
                                    INPUT Get user input
                             CMPIM $40
0510: 021B C9 40
                                    CRO
                                           If delete input
0520: 021D D0 0B
                              BNE
                                    SEQFLG and seqence flag is set
0530: 021F 24 E6
                              BIT
                                    RETURN
0540: 0221 10 46
                              RPI.
0550: 0223 A9 FF
                              LDAIM $FF
                                           then set TIMNUM flag
                                    TTMNUM
0560: 0225 85 E7
                              STAZ
0570: 0227 A9 40
                              LDAIM $40
                                           restore delete
0580: 0229 60
                              RTS
                              CMPIM SOD
0590: 022A C9 0D
                      CRO
                                           If CR
                                    RETURN
0600: 022C D0 3B
                              BNE
                                    SEQFLG and sequence flag is set
0610: 022E 24 E6
                              BIT
0620: 0230 30 24
                              BMI
                                    ENDSEQ go see what to do
                                    BASBUF otherwise look at BASBUF
0630: 0232 A5
               18
                              LDA
0640: 0234 C9 23
                              CMPIM $23
                                            did he input a #?
0650: 0236 D0 2F
                              BNE
                                    CRRET
                                            If not return with a CR
                              LDAIM $FF
0660: 0238 A9 FF
0670: 023A 85 E6
                              STAZ SEQFLG If yes set sequence flag
                              LDAIM $0D
0680: 023C A9 0D
                                            Output a CR
0690: 023E 20 17 10
                              JSR
                                    OUTPUT
0700: 0241 A9 0A
                              LDAIM $0A
                                             and LF
0710: 0243 20 17 10
                              JSR
                                    OUTPUT
0711: 0246 A2 00
                              LDXIM $00
                                           Clear HI, LO and SAVX
0712: 0248 8E E9 17
                              STX
                                    SAVX
0713: 024B 86 E8
                              STX
                                    HT
0714: 024D 86 E9
                              STX
                                    LO
0720: 024F 20 90 02
0730: 0252 A2 00
                                    SETNUM and go set up HI, LO and INCR
                              JSR
                      SETLNO LDXIM $00
                                    LINO
0740: 0254 FO AE
                                           send the first line number and return
                              BEO
0750: 0256 E0 08
                      ENDSEQ CPXIM $08
                                    CLRSEQ clear SEQFLG if not enough in buffer
0760: 0258 30 09
                              BMI
                                    INCLN otherwise add increment to line number
0770: 025A 20 C5 02
                              JSR
 0780: 025D A9 FF
                              LDATM SEF
                                           and set the TIMNUM flag
                                    TIMNUM
0790: 025F 85 E7
                              STAZ
                                    CRRET
0800: 0261 30 04
                              BMT
                                           and returns with CR in ACC
                      CLRSEQ LDAIM $00
0810: 0263 A9 00
0820: 0265 85 E6
                              STAZ
                                    SEQFLG
                              LDAIM $0D
0830: 0267 A9 0D
                      CRRET
                      RETURN RTS
 0840: 0269 60
0850:
 0860:
                        SUBROUTINES FOLLOW
                                            Puts hex byte in ACC in BASIC buffer as
0870: 026A 48
                      OUTNUM PHA
                                            2 ACII decimal digits and ehoes to user
 0880: 026B 4A
                              LSRA
0890: 026C 4A
                              T.SRA
                              LSRA
 0900: 026D 4A
                              LSRA
0910: 026E
            41
                                    HXTAS
 0920: 026F 20 7D 02
                              J3R
                                    PULIM
 0930: 0272 20 89 02
                              JER
 0940: 0275 68
                              PLA
 0950: 0276 20
               7D 02
                              JSR
                                    HXTAS
                                    PHUM
 0960: 0279 20 89 02
                              JSR
 0970: 027C 60
                              RTS
                              ANDIM SOF
                                            Changes hex character to ASCII
 0980: 027D 29 OF
                      HXTAS
 0990: 027F C9 OA
                              CMPIM $0A
 1000: 0281 18
                              CLC
 1010: 0282 30 02
                              BMI
                                    HXI
 1020: 0284 69 07
                              ADCIM $07
 1030: 0286 69 30
                      HXI
                              ADCIM $30
                              RTS
 1040: 0288 60
                                    OUTPUT Line number to buffer and output
 1050: 0289 20 17 10
                      PNUM
                              JSR
 1060: 028C 95 1B
                              STAAX BASBUF
                              INX
 1070: 028E E8
                              RTS
 1080: 028F 60
                                            Gets base line number and increment from
                       SETNUM INX
 1090: 0290 E8
                              LDAAX BASBUF buffer and places in HI, LO, and INCR
 1100: 0291 B5 1B
                              CMPIM $20
 1110: 0293 C9 20
                                    SETNUM Ignore spaces
 1120: 0295 F0 F9
                              BEO
```

page 14

1130:						CMPIM		If plus sign (+) then go get increment
1140:		_				BEQ	GETINC	
1150:				1A		JSR	PACKT	Otherwise convert to ASCII and store
1160:						LDA	LO	
1170:			04			LDYIM	\$0 4	Into HI and LO
1180:					ROT	ASLA		
1190:			E8			ROL	HI	
1200:	02A5	88				DLY		
1210:	02A6	D0	FA			BNE	ROT	
1220:	02A8	0D	E9	17		ORA	SAVX	
1230:	02AB	85	E9			STA	LO	
1240:	02AD	8C	E9	17		STY	SAVX	
1250:	02B0	4C	90	02		JMP	SETNUM	And go look for next one
1260:	02B3	E8			GETINC	INX		The second second
1270:	02B4	B 5	18				BASBUE	Get increment number
1230:	02B6	C9	20			CMPI!		oct incience namei
1290:	02B8	F0	05			BEO	, +	If blank done
1300:				1A				Convert to ASCII and leave it in SAVX
1310:						BEQ	GETINC	Go get next one
1320:				17	GOTIT	LDA	SAVX	do get hext one
1330:						STAZ	INCR	put it in INCR and return
1340:						RTS	2.1020	put it in thek and recurn
1350:			F:5		INCLN	LDAZ	INCR	Add increment amount to live workers
1360:			23		THEBU	CLC	LICK	Add increment amount to line number
1370:						SED		
1330:			τ·α				LO	would sell the source code for an
1390:								bucks).
1400:						STA	ro	
1410:						LDA	HI	The "real-time clock" is act
1420:						ADCIM		counter and not a time of day clo
			ΕŞ			STA	ΗI	useful in games etc.
1430:		-				CLD		_
144):	U ZD 4	60				RTS		PRODUCT ANNOUNCEMENT

A NEW COMMAND FOR BASIC

Dick Grabowski HDE INC.

To implement the "GET" command in KIM BASIC by Microsoft, change the following:

at location \$2AEA-\$2AEC enter AO OO A2 1A

The "GET" command allows terminal input and test of a single character without the need to enter the "RETURN" key. One example is in terminal use where you want to hold some material on the screen until the user signals completion:

1000 PRINT:PRINT "ENTER SPACE WHEN READY"; :GET A\$:
IF A\$ (2)"" THEN 1000

This will repeat the prompt "ENTER SPACE WHEN READY" until a space is entered, then fall through to the next program step. Of course, many other uses exist.

GET A ---returns the numeric value 0-9 GET A\$---returns the alpha value A-Z

Bob Kurtz of Micro-Z mentioned that he got the "GET" command working by changing location \$2AEE from \$DO to \$FO.

The GET command will simplify the user interface considerably.

PRODUCT REVIEW

by the editor

Review of Harvey Hermans Basic Enhancement Package as mentioned in Issue #13 p. 12.

Besides what I mentioned in issue #13 you also get a method for using KIMs ST key for stopping the program in a controlled manner, the ability to append Basic programs and subroutines from cassette tape, and a fix for a bug in Basics cassette save routine (also see Herr Schillings letter in the Basic section of this issue for the same fix).

For 15 bucks you get five pages of info. Four pages of explanations and sample printouts of the Basic mods and the fifth page is a hexdump of the mods.

There's no doubt that this is a useful package of info for the Basic user. My only complaints are that the price is a little steep (\$7.50 would have been more like it) and the source codes for the mods is not included (Mr. Herman indicated he

code for an additional 15

lock" is actually a "tick" e of day clock. Could be

PRODUCT ANNOUNCEMENT

Bob Kurtz of Micro-Z has announced that he is making available his Basic mods which add Hypertape and most importantly the ability to save and load Basic data as well as programs. (This is one of the shortcomings of the 6502 version of Microsoft Basic. It's hard to believe that this a-bility wouldn't be part of the original program specs.) The ability to save data is a very important one as it enables one to maintain and up-date data files of such things as income info for tax time, scores for the plant bowling league, handicaps for the local golf course, maintaining your check book, etc etc.

The package also includes a 60 + page Basic manual which explains each command in detail and includes many programmed examples. I have the manual and can attest to its completeness. only thing this manual doesn't include is any Zero-page usage data

as was found in the Basic documentation included with the Basic from Johnson Computer.

Anyhow, Micro-Z is asking \$35 for their Basic enhancement package and this uncludes the manual. Contact Micro-Z Co, Box 2426, Rolling Hills, Ca 90274

BASIC 'USR' FUNCTION INFO

C. Kingston 6 Surrey Close White Plains NY 10607

Microsoft BASIC users should note that "AYINT" does not work as described in the instructions for Microsoft BASIC (at least in my version of it.) The USR argument is returned to \$00B1(HI) and \$00B2(LO), and not to Y and A. After having some problems with the USR statement, I wrote to Microsoft and they repsonded with the above information (apparently not having had this brought to their attention before according to their letter). You should check your version out to see what it does, as newer ones may have this changed either in the program or the instructions. This is applicable for the KB-9 version. I cannot verify that the following work, but Microsoft wrote that the return is to AB(LO) and AC(HI) in KB-6, and B4(LO) and B5(HI) in the ROM version. I would check the HI-LO arrangement carefully, since they had them reversed for the KB-9 version; they work as stated above in my BASIC.

FROM THE EDITOR: The 'USR' function in Microsoft Basic is a kluge at best. Does anyone know where the 'USR' routine is located in Basic so we can make it work right. Tiny Basic has a much better machine language interface.


Do you know who you can do with your kind?


If not, we have a few suggestions . . .


Two books, whose programs are now available on computer program tapes, will give you numerous suggestions and complete directions for some unique and fun applications for your KIM.

THE FIRST BOOK OF KIM (by Jim Butterfield, Stan Ockers, and Eric Rehnke) is the book all KIM users have been waiting for. In it, you'll find a beginner's guide to the MOS Technology KIM-1 microcomputer as well as an assortment of games and puzzles including Card Dealer, Chess Clock, Horse Race, Lunar Lander, and Music Box. The authors go into detail on how you can expand your KIM from the basic small-but-powerful KIM-1 system to a huge-and-super-powerful machine. Also featured are diagnostic and utility programs for testing both the computer and external equipment (such as cassette recorders), expanding memory, and controlling analog devices. (#5119-0, \$9.95) Now available are easy-to-use computer program tapes that feature the 28 recreational and 13 utility programs found in THE FIRST BOOK OF KIM. Tape 1 (#00700) and Tape 2 (#00800) have 14 recreational programs each, and Tape 3 (#00900) has 13 diagnostic and utility programs. All three tapes are \$9.95 each.

HOW TO BUILD A COMPUTER-CONTROLLED ROBOT (by Tod Loofbourrow.) "Finally someone has written a book on robot building with microprocessor/microcomputers and a good one at that!... a gold mine of useful information on interfacing microcomputers to the real world — and beyond." Computer Dealer. You'll experience the thrill of creating an intelligence other than human when you see how "Mike" grows from totally under your control, to seeing and feeling his environment, to responding to voice commands. This book details that creation by giving step-by-step directions for building a robot that is controlled by a KIM-1. (#5681-8, \$7.95). The five complete control programs for a robot are clearly documented in the book and are available on a computer program tape. (#00100, \$14.95)







Hayden Book Company, Inc. 50 Essex Street, Rochelle Park, NJ 07662

focal

Lots of neat mods are in store for FOCAL. We're going to add a cassette save & load facility, a Basic-like data statement, output to KIM's seven segment display, the ability to handle arrays of strings, an improved print command, a machine language subroutine call and a few minor fixits and speed-up mods.

Before we do all this, however, we need some room. The present size of the Aresco V3D is about 6K so let's stretch it out to an even 8K and give ourselves a little breathing room. If you examine the listings (love them listings!), you'll notice that the user program must start right after Focal because of line number 00.00 at \$35EB.

(One problem: all these mods pertain to V3D which is distributed by Aresco and not necessarily to FCL-65E which is distributed by 6502 Program Exchange. The symbolic addressing info might pertain to FCL-65E but since I don't have a listing of FCL-65E, I can't be sure. FCL-65E might be an updated version of V3D but I can't be sure).

Extend V3D FOCAL to 8K by moving \$35EB through \$360A to \$3FEO-\$3FFF. This moves the line 0.0 startup message to the top of the 8K block that will be used by FOCAL. Some zero page pointers must also be changed to allow for the above mod.

```
change: TEXTBEG $002F FROM $EB TO $E0 $0030 FROM $35 TO $3F
         PRADE
                  $0031
                          FROM $09 TO $FE
                          FROM $36 TO $3F
                  $0032
         VARBEG
                  $003E
                          FROM $0A TO $FF
                   $003F
                          FROM $36 TO $3F
          VARST
                  $0040
                          FROM $0A TO $FF
                  $0041
                          FROM $36 TO $3F
          VAREND
                  $0042
                          FROM $0A TO $FF
                          FROM $36 TO $3F
                  $0043
                  $0053
                          NO CHANGE
          PDLIST
                         FROM $3F TO $5F
                  $0054
```

This is the FOCAL pushdown stack and should be set to some convenient page up out of the way of FOCAL programs. \$5F assumes a 16K system.

Another thing that must be improved is the way FOCAL sets up zero-page. Actually, it doesn't. I really can't understand why the implementers overlooked this problem. Oh well...it's easy to fix. At \$3F00 add the following zero page intialization routine. \$3F00 will become the new cold start address.

```
ZPAGE = $0
ZSTORE = $3F10
         LENGTH = $BF
                           : NUMBER OF BYTES
         STARTF = $2000
          *=$3F00
                        ; INITS THE LOOP COUNTER
CSTART
         LDX #0
         LDA ZSTORE.X ; START MOVING DATA
ZLOOP
         STA ZPAGE,X
         INX
         CPX #LENGTH+1
         BNE ZLOOP
                           PAGE IS SET UP
         JMP STARTF
                        ; GO TO FOCAL
```

Ok now, we have stretched out FOCAL to 8K and added a Z page initialization routine. What next? We'll start adding mods from \$35EB-\$3EFF.

More next time.....

tiny basic

Oops! In issue #13, I left out the mod that must be made to the IL at \$0A26. Here it is:

OA26 1E NX NX on REM instead of NS.

In the next issue, we'll be presenting a very comprehensive string capability for TB as well as a cassette save and load ability. (I ran out of room in this issue). Must be a good number of Tiny Basic users out there. Have you done anything neat with TB? Let us know.

forth

Nothing new to report here except that by issue #15 or #16 I hope to be announcing availability of FORTH for KIM. Preliminary versions are actually operational at this point, but documentation has to be written and other details have to be worked out. This version of FORTH was written to conform to the implementation info presented in the Caltech FORTH manual. A complete source listing will be available.

Beware - just because it's called FORTH don't mean it really is. Before you purchase any package called "FORTH" make sure it conforms to the "international standard" presented in #13.

xplo

Ready for something new? Take a look at XPLO. This is a block structured compiling language that is quite a bit different from BASIC or FOCAL and more along the lines of a subset of ALGOL or PASCAL. An article on XPLO appeared in Kilobaud (Feb 79 p. 24) which should enlighten you on the ins and outs of this new addition to the 6502 users arsenal.

I purchased XPLO from the 6502 Program Exchange, 2920 Moana, Reno NV 89509. Get their catalog for \$1. Lots of good software from this group Check them out.

Here's a sample HILO program written in XPLO to give you an idea what it looks like.

```
'INTEGER' GUESS'NUMBER', INCORRECT, TRY;
'PROCEDURE' MAKEANIMATE
'CODE' CRLF=9,RANDOM=1,INPUT=10,TEXT=12;
'BEGIN'
    NUMBER:=RANDOM(100);
'END';
'PROCEDURE'
                  INPUTGUESS:
'BEGIN'
         GUESS:=INPUT(0);
'END';
'PROCEDURE'
                 TESTGUESS;
'BEGIN'
     'IF' NUMBER=GUESS 'THEN'
    'BEGIN'
         TEXT(0, "CORRECT!!");
         TRY:=1;
    'END'
    'ELSE'
         'IF' NUMBER<GUESS 'THEN'
         TEXT(0, "TOO HIGH")
         'ELSE' TEXT(0, TOO LOW");
CRLF(0);
'END';
'BEGIN'
INCORRECT:=0;
TRY:=INCORRECT;
MAKEANUMBER #
WHILE TRY=INCORRECT 'DO'
              BEGIN'
                      TEXT(0, GUESS ");
                      INFUTGUESS?
                      TESTGUESS;
             'END';
```

The 6502 Program Exchange also offers a very powerful text editor which is based on the DEC TECO editor. TEC65 is a line oriented (no line numbers) and allows for some very complex editing editing macros. For instance, you could conceivably convert an assembly source file from one assembler format to another. TEC65 includes a cassette operating system which lets you save and load text files.

I've had this editing language running on my machine and am quite impressed with its power. Check it out! page 17



ACCESSING THE SYM DISPLAYS

A. M. Mackay 600 Sixth Avenue West Owen Sound, Ontario

I got my new SYM-1 a couple of weeks ago, and I love it. But there's a lot of work to be doneit's not that similar to KIM.

Outputting on the display is a lot differentinstead of using F9, FA and FB, you have to treat each 7-segment display as a unit, and get it into DISBUF at A640 (left display) through A645 (right display). But since DISBUF is in write-protected RAM, you have to call ACCESS at 8B86 first to unwrite the RAM.

I've enclosed a little SYM-1 program to output the characters, and shown the segment coding. The program as written will display squirrely characters as indicated. Any character can be displayed by changing the coding in 021A through 021F using the indicated coding, and others can be found starting at location 8C29 in the monitor.

This program may help novices like myself to get the feel of SYM. I haven't had time to figure out the counter yet.

Maybe some bright USER can come up with a way to hook up Don Lancaster's TVT 6 5/8 to a SYM.

Sorry that Jack Cowan had trouble with his Solid State 4K board. Mine worked the first time with my KIM (no bad chips), and when I plugged it into my SYM, after changing the addresses, it also worked perfectly.

ACCESS \$8886 DISBUF \$A640-45 SCAND \$8906 0200 A2 05 LDX @ O.5 20 86 8B GETCH 0200 ACCESS JSR BD 14 02 LDA TABLE.X DISBUF.X 9D 40 A6 STA 0208 020B CA DEX GETCH 10 F7 020C BPL 20 06 89 SCAND 020E DISPL JSR 4C OE 02 0211 JMP DISPL 0214 TABLE .BYTE 'ESCAPE' 0215 6D 0216 0217 77 0218 73 0219 Blank = 00, Decimal = 80

3 D	ū	or	37	Π
76	Н		64	٦
1 E	ų		52	ب
38	þ		D3	킾
73			49	=
3E	Ц		5 C	_

SEGMENT CODE

Other character codes start at Mon. address \$8029. To change display change coding in table 0214-0219.

SYM NOTES & KIM-4 COMPATIBILITY

C. Kingston 6 Surrey Close White Plains NY 10607

I note that some information on the SYM is being included in the 'USER NOTES'. The SYM looked like a reasonable way to improve a KIM based system so I looked into this. The Synertek liturature states that the SYM is usable with any KIM based motherboard. To check, I wrote Synertek and asked specifically if it would work with the KIM-4. They replied that it would. So I got one and tried it, and can report that it does not work with the KIM-4. The trouble was tracked down to the fact that the KIM-4 data buffers are enabled at the wrong times. Thus the KIM-4 has to be altered for proper decoding. After cooling down page 18

somewhat about this development, I looked into the problem and came up with a solution, but not an optimal one.

The following alteration will result in the KIM-4 being enabled for all addresses below \$8000, and disabled for all above (and including) \$8000. Since the SYM in its full glory will utilize almost all of the addresses above \$8000, this scheme makes sense. However, if you want to fit in some RAM in the unused high memory positions, you will have to resort to more extensive surgery on the KIM-4. The mod here requires that the lower 1K of memory be on the KIM-4, which makes the RAM on the SYM unnecessary. A simple change will disable the low 1K (\$0000-\$03FF) on the KIM-4 and allow its use on the SYM. However, since this makes filling in the rest of the first 8K somewhat awk-ward, I prefer to ignore the SYM RAM (which should be removed, especially if either set of RAM's on the same address can be write protected.)

First of all, you will have to remove chip U5 of the KIM-4 (the 7423) and replace it with a socket. Since you will in all probability destroy U5 in this process, be sure you get another 7423 before starting. Note that some pins make their connection at the top of the board only. If a tiny bit of solder is placed on these pins at the base before putting the socket on the board, it will melt and make contact if you heat the pin adequately. Replacing the 7423 into the socket will leave the KIM-4 in its original state for the KIM.

Now you will connect a 16 pin dip header to a 14 pin socket using the following connections:

16 PIN	(TOP)	14 PIN	(BOT)
4		9	
6		12	
7		8	
8	GND	7	GND
9		3	
10		2	
12		1	
16	VCC	14	VCC

Now connect pins 10 and 11 together on the 14 pin socket, and do the same with pins 13 and 14. Be sure to use covered wire as they will have to cross over each other. I made my connections about ½ inch long so that the 14 pin socket sets just above the 16 pin dip header. Using solid hookup wire makes for a fairly firm package. Being careful to observe the location of pin 1, put a 7400 (or 74LS00) into the 14 pin socket. Now plug the converter into the socket for U5 in place of the 7423. The KIM-4 is now enabled for the lower 32K and disabled for the top 32K. The SYM should now work when plugged in, but not the KIM.

To disable the KIM-4 for the first 1K, do not connect pins 13 and 14 on the 14 pin socket together. Instead, run a connection from KO on the applications connector (pin A-B) to pin 13 of the 14 pin socket. Note that there is an unused nand gate in the 4700 that can be used for additional coding if desired. (The info in this paragraph has not actually been tried yet).

Having made the above conversion, I was then in a position to determine whether or not KIM programs that use TTY or CRT I/O could be successfully transferred and used after changing the I/O vectors and/or JSR's. This led to the next problem. Transferring programs to the SYM system from the KIM system sounds easy since SYM has a KIM format tape input program. But it ain't easy. First of all, as noted in the Feb ('79) MICRO, the SYM stops when it detects a '2F', thinking it is the end of file marker. Those '2F' bytes that are not EOF's have to be changed to something else before transfer, and then changed back afterwards. intend writing a short program that will do this in the near future.) The next problem is that SYM will not read tapes made with Hypertape; you must muse the KIM monitor speed. I suppose that a program could be written to read Hypertape, and wonder why Synertek didn't make theirs flexible enough to do this. (If I read the monitor proram correctly - and this is not easy to do because of all the branches and jumps it uses - the number of pulses required per bit is programmed into the monitor and cannot be changed.)

SYM-1. Finally, a dependable microcomputer board.

In performance. In quality. In availability. OEMs, educators, engineers, hobbyists, students, industrial users: Our Versatile Interface Module, SYM-1, is a fullyassembled, tested and warranted microcomputer board that's a true single-board computer, complete with keyboard and display. All you do is provide a +5V power supply and SYM-1 gives you the rest—and that includes fast delivery and superior quality.

Key features include:

- Hardware compatibility with KIM-1 (MOS Technology) products.
- Standard interfaces include audio cassette with remote control; both 8 bytes/second (KIM) and 185 bytes/second (SYM-1) cassette formats; TTY and RS232; system expansion bus; TV/KB expansion board interface; four I/O buffers; and an oscilloscope single-line display.

To place your order now, contact your local area distributor or dealer.

OEM Distributors

Kierulff Electronics Sterling Electronics (Seattle only) Zeus Components Century/Bell Lionex

Hallmark Intermark Electronics Quality Components Technico General Radio Western Microtechnology Future Electronics Alliance Electronics Arrow Electronics

Personal Computer Dealers

Newman Computer Exchange Ann Arbor, Michigan

- 28 double-function keypad with audio response.
- 4K byte ROM resident SUPERMON monitor including over 30 standard monitor functions and user expandable.
- Three ROM/EPROM expansion sockets for up to 24K bytes total program size.
- 1K bytes 2114 static RAM, expandable to 4K bytes on-board and more off-board.
- 50 I/O lines expandable to 70.
- Single +5V power requirements.
- Priced attractively in single unit quantities; available without keyboard/display, with OEM discounts for larger quantities.

Synertek Systems Corporation.

150-160 S. Wolfe Road, Sunnyvale, California 94086 (408) 988-5690.

Technico Columbia, Maryland Computerland Mayfield Heights, Ohio **RNB** Enterprises King of Prussia, Pennsylvania Computer Shop Cambridge, Massachusetts Computer Cash Anchorage, Alaska

Ancrona Culver City, California General Radio Camden, New Jersey Advanced Computer Products Santa Ana, California Computer Components Van Nuys, California Altronics San Jose, California

I finally managed to transfer Tiny Basic to the SYM system, and after changing the I/O vectora, found that it worked. One point that I noted was that the SYM monitor converts lower case input into upper case, but this looks like it would not be too hard to get around.

Another point of difference in the KIM and SYM. I have found the KIM tape I/O to be extremely reliable and not critical in the recorder used or the settings used. For the short bit that I have used the SYM, I have found it to be extremely sensitive to the recorder volume and tone settings, particularly for the high speed format. It was thoughtful of Synertek to provide a visual means of setting the volume and tone controls for proper reading of the tape (using a sync tape). I guess one must decide which is better - fast tape 1/0 but critical settings, or slower but surer tape I/O.

ADDENDUM

Since writing the above I have noted another problem in using the SYM with the KIM-4. KIM outputs K1,2,3,4 are wire-or'd together on the KIM-4 and pulled up with a resistor (R2). The equivalent lines on the SYM are not open collector lines and probably should not be wire or'd. No harm came to the 74LS138 on the SYM during the short time I used it without noticing this (at least no noticeable harm). These four lines can be separated on the KIM-4 by cutting the traces between them (where the connectors are soldered to the KIM-4 board). K4 (A-F) can be disconnected from R2 by removing the through plating where the line transfers to the bottom of the board. A four position dip switch could be hooked up to connect or disconnect the lines.

WUMPUS & MUSIC BOX MODS FOR SYM

Jim Adams 17272 Dorset Southfield, Mi 48075

SYM Users: Make the following modifications to Stan Ockers' WUMPUS program in The First Book Of KIM to use it on your machine.

1	LOC	FROM	TO							
:	35C	E 7	29							
:	35D	1 F	8 C							
:	365	E 7	29							
:	366	1 F	8 C	~						
	376	14	47	ASCII	G	(GO	key)	to	pitch	Gas
:	2 A 6	06	04				•		-	
	2A7	17	A 4							
:	2E1	E7	29							
	2 E 2	1F .	8 C							

Replace 200 thru 257 with

200	84	DE	85	DD	20	86	8 B	ΑO	05	B 1	DD	49	80	C 9	80	F0
210	1 F	99	40	A 6	88	10	F 2	A 2	0 A	86	DB	A 9	52	8 D	1 F	Α4
220	20	06	89	2 C	06	A 4	10	F8	C 6	DB	D0	ΕF	E 6	DD	D0	D 7
220	40															

Replace 258 thru 271 with 258 20 AF 88 C9 47 F0 05 20 75 82 B0 F4 60

Make the following modifications to Jim Butterfield's MUSIC BOX program in The First Book Of KIM to play music on your on board speaker.

LOC	FROM	TO	
20B	BF	OD	
20C	8 D	20	
20D	43	A 5	
20E	17	89	
219	00	60	
24C	A 7	06	ATTENTION "VIM" AND "AIM-65" USERS!!
255	27	8 0	THE SAN FERNANDO VALLEY KIM-1 USERS
270	42	02	CLUB IS EXPANDING ITS MEMBERSHIP TO
271	17	A 4	INCLUDE THESE THO NEW AND EXCITING MICROCOMPUTER SYSTEMS WE MEET AT 7:3 PM ON THE SECOND WEDNESDAY OF THE
e 20			MONTH AT 28224 COHASSET #16, CANOGA PARK, CR 91306, CALL JIM ZUBER AT (213

341-1610 IF YOU HAVE MY QUESTIONS.

7:30



Jody Nelis K317h 132 Autumn Drive Trafford Pa 15085

I have had a Rockwell AIM 65 for three weeks now and I can only say one thing: Fantastic machine!!!

The AIM is following a one year session with a KIM-1. The 8K monitor in the AIM takes care of a lot of the things that the KIM monitor needed additional software to handle.

The text editor is slick especially for we typists who make a lot of mistakes. Entering a program in mnemonics is a step up from all Hex Op

The user's guide shipped with the AIM was hurridly put together since it held up shipment of the hardware. To help others who may have an AIM 65, I'm passing along several items that I believe to be incorrect in the user's guide (October 1978 issue).

- Page 2-19 A step is missing in the program entry for this example. Between the "AND #0F" and the "BRK" there should be a "STA
- Page 2-25 At the top of the page, the display register format should read: PC P A X Y S
- Page 3-20 There is a problem with the form given for the (indirect), Y addressing mode. See the separate sheet that discusses that subject.
- Page 3-23 Under using the K command:
 1. Type K. AIM 65 will repsond with: <K>*=
 - Enter the starting address in hexadecimal. AIM 65 will respond with:
 - Type return. AIM 65 will respond with: /
 - 4. Specify the number of instructions.. ETC.
- Page 9-11 The syn test pattern program has multiple errors in it. This is liable to have a lot of people wearing out VR1 or spending a lot of time trouble-shooting an OK tape recorder. I have included a corrected program disassembled from the AIM 65 on a separate sheet.
- Page 11-3 The Olivetti type no. 295933R35 thermal paper that is refered to can't be located in the Pittsburgh area using that number. In fact all of the Olivetti Dealers I talked to were unable to come up with any 2½ inch wide paper at all. I have found that Texas Instruments #TP-27225 thermal paper is the right size and price (3 rolls for \$3.69) and is available anywhere that TI calculators are sold. I haven't tried the SEARS paper yet but the catalog at least says it exists. In a pinch, Radio Shack sells 3 smaller rolls for \$2.79 that will work also (Cat. No. 65-706).
- Page A-1 There is a problem with the form given for the (indirect), Y addressing mode. See the separate sheet that discusses that subject.
- Page K-10 The disassembly listing on this page and the next have been interchanged.

Hopefully these corrections will aid any other new AIM owners get aquainted with their machine,

KIM" BUS EXPANSION!

AIMTM, VIMTM, (SYM)TM, KIMTM OWNERS (and any other KIMTM bus users) buy the best 8K board available anywhere:

GRAND OPENING SPECIAL!

HDE 8K RAM-\$169! 3 for \$465!

Industrial/commercial grade quality: 100 hour high temp burnin: low power: KIM bus compatible pin for pin: super quality & reliability at below S-100 prices (COMMERICALLY rated S-100 boards cost 25-75% more). When you expand your system, expand with the bus optimized for 8 bit CPU's, the Commodore/Mos Technology 22/44 pin KIM bus, now supported by Synertek, MTU, Rockwell International, Problem Solver Systems, HDE, the Computerist, RNB, and others!

KIM-1 computer \$179.00: KIM-4 Motherboard \$119: power supply for KIM-1 alone—\$45: enclosure for KiM-1 alone \$29: HDE prototype board with regulator, heatsink, switch address & decoding logic included \$49.50: book "The First Book of KIM" \$9.95: book "Programming a Microcomputer: 6502" \$8.95: SPECIAL PACKAGE DEAL; KIM-1, power supply, BOTH books listed above, ALL for appear

HDE FILE ORIENTED DISK SYSTEM (FODS) FOR KIM BUS COMPUTERS Make your KIM (or relative) the best 6502 development system available at any price. Expand with HDE's full size floppy system with FODS/Editor/Assembler. 2 pass assembler, powerful editor compatible with ARESCO files KIM bus interface card: fast 6502 controller handles data transfer at maximum IBM single density speed for excellent reliability: power supply for 4 drives: patches to Johnson Computer/Microsoft BASIC. 45 day delivery. Single drive—\$1995 dual drive \$2750

Shipping extra unless order prepaid with cashier's check ALL items assembled, tested, quaranteed at least 90 days.

PLAINSMAN MICRO SYSTEMS (div. 5C Corporation)
P.O. Box 1712, Auburn, Al. 36830: (205)745-7735
3803 Pepperell Parkway, Opelika
[1-800-833-8724] Continental U.S. except Al.
Dealers for OSI, COMMODORE, COMPUCOLOR,

VISA" ALTOS





HUDSON DIGITAL ELECTRONICS, INC.

BOX 120, ALLAMUCHY, N.J. 07820 • 201-362-6574

KIM-1 PRODUCTS FROM HDE, INC.

DM-816-M8 8K STATIC RAM MEMORY

This is the finest memory board available for the KIM-1 at any price. Commercial/Industrial quality. All boards are continuously operated and tested for a minimum of 100 hours prior to release. Full 6 month parts labor warranty.

DM-816-DI1 8" FLEXIBLE DISK SYSTEM

Available in single and dual drive versions. Includes interface card, power-supply, Sykes controller and drive, cables and manual. File Oriented Disk System software with HDE text editor.

DM-816-MD1 5" FLEXIBLE DISK SYSTEM

Single and dual drive versions include interface/controller, power supply, Shugart drive, cables and manual. Advanced version of FODS software with HDE text editor, Latest addition to HDE peripheral product line.

DM-816-CC15 MOTHER BOARD

A professional mother board for the KIM-1. All KIM-1 functions remoted, includes power on reset, 15 connectors. Provision for Centronics printer interface. Card cage and cabinet configurations available.

DM-816-UB1 PROTOTYPE CARD

Designed for ease of special applications development. Handles up to 40 pin dips.

HDE ASSEMBLER

An advanced, two pass assembler using 6502 cross-assembler mnemonics. Free form, line oriented entry. Directives include: .OPTION, .BYTE, .WORD, .FILE, .OFFSET, .END. Output options include: LIST, NOLIST, SYMBOLS, NOSYMBOLS, GENERATE, NOGENERATE, ERRORS, NOERRORS, TAB, NOTAB. Assemble from single or multiple source files. Place source, object and symbol table anywhere in memory. Automatic paging with header and page number. User's manual. Approximately 4K. Loads at 2000 or E000. Specify on order.

HDE TEXT OUTPUT PROCESSING SYSTEM (TOPS)

A comprehensive output processor, including left, right and full justification, variable page length, page numbering (Arabic or U/C and L/C Roman), page titling, string constants, leading and trailing edge tabbing, field sequence modification, selective repeat, selective page output and much more. Over 30 commands to format and control output of letters, documents, manuscripts, User's manual, Approximately 4K, Loads at 2100 or E100. Specify on order.

HDE DYNAMIC DEBUGGING TOOL (DDT)

Built in assembler/disassembler coupled with program controlled single step and dynamic breakpoint entry/deletion facilitates rapid isolation, identification and correction of programs under development. Keystrokes minimized with single letter, unshifted commands and optional arguments. User's manual. Approximately 2K. Loads at 2000 or E000. Specify on order.

HDE COMPREHENSIVE MEMORY TEST (CMT)

Eight separate diagnostic routines test for a variety of memory problems. Each diagnostic, the sequence of execution, the number of passes and halt/continue on error is selected by the user on call-up. Tests include pattern entry and recall, walking bit, data-address interaction, access time and cross talk. simulated cassette load, slow leaks, Suitable for static and dynamic ram, User's manual, Approximately 3K, Loads at 2000 or E000. Specify on order.

HDE TEXT EDITOR (TED)

Complete, line oriented text editor accepts upper or lower case commands. Functions include line edit, line move, line delete, block delete, resequence, append, list, print, locate, set, scratch, automatic/semi-automatic line numbering, lastcommand recall, job command. This editor is supplied with all HDE Disk Systems. User's Manual. Approximately 4K. Loads at 2000 or E000. Specify on order.

ALL PROGRAMS ARE AVAILABLE FOR LOCATIONS OTHER THAN THOSE SPECIFIED AT ADDITIONAL CHARGE.

	Disk-Note A	Cassette-Note B	Manual Only	Note C				
HDE Assembler	\$ 75.00	\$ 80.00	\$ 5.00	\$25.00				
HDE Text Output Processing System (TOPS)	135.00	142.50	10.00	15.00				
HDE Dynamic Debugging Tool (DDT)	65.00	68.50	5.00	5.00				
HDE Comprehensive Memory Test (CMT)	65.00	68.50	3.00	5.00				
HDE Text Editor (TED)	N/C	50.00	5.00	15.00				
Note A. Media charge \$8.00 additional per order. Save by combining orders								

Media charge \$8.00 additional per order. Save by combining orders.

Note B. Cassette versions available 2nd qtr. 1979.

Note C. Additional charge for object assembled to other than specified locations.

ORDER DIRECT OR FROM THESE FINE DEALERS:

JOHNSON COMPUTER Box 523 Medina, Ohio 44256 216-725-4560

PLAINSMAN MICROSYSTEMS Box 1712 Auburn, Ala. 36830 800-633-8724

ARESCO P.O. Box 43 Audubon, Pa. 19407 215-631-9052

Corrected SYN test pattern program

END

/03 0300 20 JSR F21D 0303 20 JSR F24A 0306 4C JMP 0303

<K>*=0310
/11
0310 A2 LDX #00
0312 A9 LDA #CE
0314 20 JSR EF7B
0317 20 JSR EDEA
031A A2 LDX #00
031C A9 LDA #D9
031E 20 JSR EF7B
0321 20 JSR EF7B
0321 20 JSR EE29
0324 C9 CMP #16

0326 FO BEQ 0321

0328 DO BNE 0310

CONTRADICTIONS & CONFUSION IN THE TABLES OF ADDRESSING MODE FORMATS FOR USE WITH THE AIM 65 MNEMONIC ENTRY MODE

On the AIM 65 Summary Card:

The operand format given for the (indirect),Y addressing mode is incorrect. Both the (HH,Y and the (HH,Y) formats, when entered, end up being decoded as an (indirect,X) opcode. Needless to say, this bombs a program badly!!

In the AIM 65 User's Guide on page A-1:

The same comments as above apply.

In the AIM 65 User's Guide on page 3-20:

One of the operand formats given for the (indirect), Y addressing mode is correct here. The (HH)Y works fine. The (HH,Y) format given here is no good as noted above.

SUMMARY:

The (HH)y operand format on page 3-20 is the only one given that runs properly. By experimentation, I have also found that (HH),Y also works and should be listed as the alternate for those who like it longer but correctly written.

I also noted that all three of the sources of information on the mnemonic instruction operand listed above have an addressing mode listed as (absolute indirect). I'm no expert on the 6502, but I know of no such addressing mode!!

(EDITORS NOTE: What about JUMP INDIRECT?)

VIDEO & TVT-6

by Mike Firth 104 N St Mary Dallas Tx 75214

I am using a Polymorphics Video Interface with my KIM-1. My purpose here is to describe what I did to make it work (besides spend money), which was simpler (except for my mistakes) than I thought it would be. Some of what I have to say will be applicable to using an S100 memory board, since the VDM is memory mapped.

I selected the Polymorphics board because, at the time, it was the only display that would give me both upper and lower case (which I needed for editing) along with graphics. I felt for my purposes, graphics would be more useful than the reversed background offered on other \$100 boards. (Besides I have worked on terminals with white background and the glare bothers me.) I also wanted to have the option of displaying control characters, which SWTC and other TVT's usually





SOFTWARE AVAILABLE FOR F-8, 8080, 6800, 8085, Z-80, 6502, KIM-1, 1802, 2650.

EPROM type is selected by a personality module which plugs into the front of the programmer. Power requirements are 115 VAC, 50/60 HZ at 15 watts. It is supplied with a 36 inch ribbon cable for connecting to microcomputer. Requires 1 ½ I/O ports. Priced at \$145 with one set of software, personality modules are shown below.

Part No.	Programs	Price
PM-0	TMS 2708	\$15.00
PM-1	2704, 2708	15.00
PM-2	2732	25.00
PM-3	TMS 2716	15.00
PM-4	TMS 2532	25.00
PM-5	TMS 2516, 2716, 2758	15.00

Optimal Technology, Inc.

Blue Wood 127, Earlysville, VA 22936 Phone 804-973-5482

don't. I wanted software control.

The graphics on the Polymorphics board consists of using the lower six bits of the word to each control one small square fitted in three rows of two each that fill all the space taken by a letter. That means the graphics fit edge to edge. One letter character (1111111) fills a portion of the block, like typing capitals on top of each other, thus .

One problem with the graphics is that some strange early decision decided that having bit 7 (most significant bit) set (=1) would be ASCII character, while unset (=0) would be graphics. One could add and remove the bit with software, but I am going to invert the data line to the video board so tests, et.al. are easier.

Any \$100 board provides many control lines because of the way the 8080 accesses memory and I/O. The 8080 requires separate data in and data out buslines and also must allow for I/O Ports that are activated with address lines and an a PINT line. That also means that there has to be a control for memory read and another for memory write, which there is. Also, since the 8080 is an early device, really odd blips can appear on the address lines while the CPU is internally working, so there are timing restrictions.

We are fortunate because the address lines stay valid for the entire clock cycle and because the data lines are bi-directional. Since the video board has both in and out buffered, we can just tie the appropriate lines (eg. bit 7 in and bit 7 out) together.


The RAM R/W line from the KIM turns out to be the only line we need to control the access to the video board. IF WE ARE WILLING TO ADD A COUPLE OF JUMPERS ON THE BOARD AND CUT TWO TRACES, we don't need any chips off the board. (What I am about to describe can be done off the board, sort of.) All of the changes take place in a one inch square area on the board.

We take advantage of an unused gate in IC9, a 74LS00, and we cut a trace to take advantage of another gate originally used as an invertor. The other trace to cut is the one that controls the data bus from the board to the computer. As wired, it is always connected, except during a write, when it goes tristate. By installing a jumper, it will be tristate except when the video board is actually addressed.

(Editors Note: The I.C. numbers and the pinout refer to an early model of Polymorphics VTI-64 Video Board. I have the Rev 'F' version and had to do some transposing of I.C. numbers and pinouts, but got everything working OK.)

As shown on the circuit, BS- goes low when the proper lK of memory is addressed. This is inverted through IC9A, then is usually NANDed with 8080 memory write to control the data buffers into the board. We are going to replace MWR+.

We bring in the KIM RAM R/W line on pin 47 to IC9C as usual. But if this is all we did, the inverted signal would messup the video display EVERY TIME WE DID A WRITE OPERATION ANYPLACE. So, we cut the trace to pin 5 if IC9 and run a jumper from pin 11 to pin 5 of IC9 (arn't we intimate). This insures that pin 6 is low only during access to this block. We then install a jumper from IC9 pin 6 to IC8 pin 3, which controls the tristate (and is next to IC9).



MODS TO POLYMORPHIC YTI-64

JUMPERS TO INSTALL

Two more jumpers remain. One goes from pin 4 of IC9 to pin 1, carrying the RAM R/W signal to the unused gate in IC9 to use it as an invertor. The output of IC9D (pin 3) is jumpered to IC9B (pin 9) to replace the 8080 MWR+ mentioned earlier. Also, pin 2 of IC9 has to be jumpered to +5 (better practice) or to pin 1.

And that is that. Connect the video board to a monitor, plug everything in and wait. The Polymorphics manual suggests aid for the board. If you get a good stable display, write a program that will load a regularly varying bit pattern into successive locations. If the display shows the same character repeated 2 times, or four times, you probably have miswired something and lost a data line or two (I did, two lines were on the wrong pins on the \$100 connector). If you can't access a part of the screen, or the program writes over some areas and doesn't touch others, then an address line is buggy. You should note that even if you only have 16 lines 32 characters long (512 characters), the video board takes up 1K of memory, since it is A5 that is ignored. This save rewriting some software if you add the other 32 later.

With KIM, you can use the monitor to load (and read) any location one-by-one. KIM accesses the memory periodically, which you will note as a line on the screen which disappears if you access elsewhere.

TVT-6 NOTES & RAM EXPANSION

by Milan Merhar 697 Boylston St Brookline Ma 02146

More TVT-6 stuff and another way to fill the lower 4K hole in KIM.

I read the letter in #13 re the TVT-6 and I thought 1'd pass along some comments.

My cassette copy of the TVT-6 programs from PAIA were very corrupt. Obviously, they were keyed in, not checked, and recorded. Check the programs against the listings before running.

One listing error for the cursor routine: the contents of \$0185 should be \$03 rather than \$01.

Dennis Chaput's problems with the cursor routine not working can be traced to Don Lancaster's cryptic note at the end of the cursor program listing: "To protect page entry, load 00F3 04, to enable page entry, load 00F3 00".

This initializes the accumulator to 04 or 00 via KIM's monitor at run time and therefore $\underline{\text{Does}}$ $\underline{\text{Nothing}}$!

Obviously, Lancaster meant to initialize 00F1 to 04 or "initialize the status byte to disable interrupts" to protect the page and initialize 00F1 to 00 or "enable interrupts" to access the cursor routine normally.


Also note that "Erase to end" and "Sparehook" comments are reversed in the cursor program commentary. ASCII 13 is "erase to end of line", ASCII 12 is "space".

If you're running Tiny Basic or the TVT-6 from low memory, you usually want to expand memory at low addresses rather than start all over again at 2000 hex and up. Most suggestions to squeeze 4K of RAM into the lowest memory space involves fancy bussing of individual chip selects to each 1K of RAM to be added. There's an easier way!


Set your commercially available 4K memory board to fill addresses 0000 hex to 0FFF hex and move KIM's 1K RAM to addresses 1000 hex to 13FF hex.

This gives 5K of contiguous RAM for use with Tiny Basic at 0200 hex or such.

The mod requires a jumper wire and one $1000\,\mathrm{ohm}$ resistor to be added.



Please note that "page zero" and the stack are now physically in the 4K RAM board which must be present for the monitor to function. Incorporating this mod to the mods for the TVT-6 gives something like this:



The SPDT switch selects whether the KIM 1K RAM is at 0000 hex to 03FF hex (with the 4K RAM removed!) or at 1000 hex to 13FF hex (with the 4K RAM present)

The DPDT switch is for normal use with the TVT-6 out of its socket.

The TVT-6 can be wired up to the 4K board as discussed by Michael Allen in #13 or can work out of KIM's 1K RAM at 1200 hex to 13FF hex. Patches are simple: The SCAN routines work is written: the cursor is changed by adding 10 hex to the contents of these locations: 0106, 010A, 016E, 0185, 01AO, 01C7, 01DC.

If you are using Tiny Basic, move the cursor routine to 1100 hex and Tiny Basic can have 1½K for user programs from 0B00 hex to 10FF hex. Make sure to initialize Tiny's program space pointers to keep from overwriting your cursor program & display memory in a normal "cold start".

INTERFACING TO THE TVT-II

by John M. Rensberger 1920 NW Milford Way Seattle Wa 98177

The KIM-1 TTY input and output interface nicely and simply with the CT 1024 TV Typewriter II. However, discovering how to effect this was not easy. MOS Technology supplies no information in their otherwise very extensive literature.

I finally discovered, after 50 hours of searching for a problem in the serial interface and UART of the TVT II, that there is no parity bit, the 8th bit is a 1, and the polarity of the signal as it comes from the transistor interface of Rick Simpson (July User Notes Vol 1) is inverted with respect to the RS232 input requirements of the TVT II serial interface.

Therefore, users attempting to make this interface should use or beware of the following conditions:

- 1. Omit the inverter in Simpson's circuit.
- 2. Program the serial interface of the TVT II for $\underline{N0}$ parity, bit 8=1.

- I used neither ground nor the -5 volt option on Simpson's circuit, (EDITORS NOTE: I didn't understand this one).
- 4. Lower the resistence of the RS232 input of the TVT serial interface by replacing R-19 (1K) with a 300 resistor.

Knowing the correct bit pattern and that the polarity from the KIM system is correct without inversion should make the interfacing task very simple for anyone wishing to use a TV typewriter as a terminal.

Gary and Lisa Rensberger (ages 14 and 16) have completed a machine language program for KIM that will work with either TVT II or TTY. They would be delighted to hear from users who would like a TIC-TAC-TOE game (700 bytes) in exchange for any other game (listing or KIM compatible tape).

CASSETTE stuff

MAKE A SHORT CASSETTE

Ted Beach - K4MKX 5112 Williamsburg Blvd. Arlington Va 22207

Regarding your search for C15 tapes, I gave up on that idea long ago. Instead, what I started to do originally was buy "cassette repair kits" sold by Lafayette Radio for about 69 cents each. These are tape housings with a leader from spool to spool. I then spliced in my required length of tape which I cut off of a good quality C60 tape. Radio Shack and Lafayette both have inexpensive (about \$4.00) cassette splicing machines.

That drill got a bit expensive, so I started buying "EI Cheapo" drugstore tapes (three C30's for \$1.29) and discarding the tape from the housings. Works real neat. Now I record the desired number of programs or subroutines on my good C60 tape, run off another foot or so of tape, then clip the tape in the center of the middle opening (where the pressure pads are). Then I pull both ends of the tape out and splice the end coming from the takeup spool to the leader going to the supply spool of El Cheapo cassette (tape already discarded).

A pencil stuck in the hub of the supply spool will quickly rewind the tape into its new housing. At the end, cut the tape from the original leader, splice it onto the leader of the takeup spool of the new housing and reconnect the free end of the C60 tape to its takeup leader. You will eventually run out of takeup leader on your "good" tape, but what the heck - tape is cheap!

As an alternative, you can allow a foot or so of the beginning of the original tape to be used as a leader (mark it with a marker pen and don't start recording until this part is on the takeup spool). This way you can get amximum use from the good tape by sacrificing a foot of it to begin with. When you're through, you will have another empty cassette housing to use, with full length leaders.

CASSETTE DIRECTORY PRINTOUT PROGRAM

Chris McCormack
...prints your tape direct- 116 Milburn Lane
ory on your TTY or terminal East Hills, NY 11577

This program is an expansion of the directory program, written by Jim Butterfield. The advantage of this program is that it will search a whole tape, and output the ID, starting address, and ending address of any program found. Because all of the branches are (EXC 0037) relative, the program is completely relocatable. Program start is at address 005F.

0000	D8			TOP	CLD	
0001	Α9	07			LDA	#\$07
0003	8 D	42	17		STA	SBD
0006	20	41	1 A	SYN	JSR	RDBIT
0009	46	F 9			LSR	INH
000B	05	F 9			ORA	INH

8.		F 9			STA INH
				TST	CMP #'SYN
. D(0	F 3			BNE SYN
		24	1 A		JSR RDCHT
C C	6	F9			DEC INH
3 10	0	F 5			BPL TST
C	9	2A			CMP #'*
. D(0	F1			BNE TST
. A:	2	FD			LDX #\$FD
) 20	0	F 3	19	RD	JSR RDBYT
3 9	5	FC			STA POINTH+1,X
5 E	8				INX
5 3	0	F8			BMI RD
8 A	2	02		MORE	LDX #\$02
A 2	0	24	1 A	SECOND	JSR RDCHT
D C	9	2 F			CMP #'/
F F	0	09			BEQ OUT
1 C	A				DEX
	_	F6			BNE SECOND
2 D	U	r u			
		EA	19		JSR INCVEB
	0	EA 28	00		JSR INCVEB JMP MORE
4 2	0	EA 28		MUST BE C	JSR INCVEB JMP MORE CHANGED IF RELOCATED)
4 2 7 4	O C	EA 28	00	MUST BE C	JSR INCVEB JMP MORE CHANGED IF RELOCATED) LDA INH
4 2 7 4 A A	0 C	EA 28 (1	00 NOTE:	MUST BE C	JSR INCVEB JMP MORE CHANGED IF RELOCATED) LDA INH JSR PRTBYT
4 2 7 4 A A C 2	0 C 5	EA 28 (19 F9	00 NOTE:	MUST BE C	JSR INCVEB JMP MORE CHANGED IF RELOCATED) LDA INH JSR PRTBYT JSR OUTSP
4 2 7 4 A A C 2 F 2	0 C 5 0	28 (N F9 3B 9E 9E	00 10TE: 1E 1E 1E	MUST BE C	JSR INCVEB JMP MORE CHANGED IF RELOCATED) LDA INH JSR PRTBYT JSR OUTSP JSR OUTSP
4 2 7 4 A A C 2 F 2 2 2	0 C 5 0	EA 28 (N F9 3B 9E	00 NOTE: 1E 1E	MUST BE C	JSR INCVEB JMP MORE CHANGED IF RELOCATED) LDA INH JSR PRTBYT JSR OUTSP JSR OUTSP JSR PRTPNT
4 2 7 4 A A C 2 F 2 2 2 5 2	0 C 5 0 0	28 (N F9 3B 9E 9E	00 10TE: 1E 1E 1E	MUST BE C	JSR INCVEB JMP MORE CHANGED IF RELOCATED) LDA INH JSR PRTBYT JSR OUTSP JSR OUTSP JSR PRTPNT CLC
A A A C 2 F 2 2 2 5 2 8 1	0 C 5 0 0 0 0 8	28 (N F9 3B 9E 9E	00 NOTE: 1E 1E 1E 1E	MUST BE C	JSR INCVEB JMP MORE CHANGED IF RELOCATED) LDA INH JSR PRTBYT JSR OUTSP JSR OUTSP JSR PRTPNT CLC LDA VEB+1
4 2 2 7 4 A A A C 2 2 F 2 2 2 5 2 8 1 9 A	0 C 5 0 0 0 8 D	EA 28 (N F9 3B 9E 9E 1E	00 NOTE: 1E 1E 1E 1E	MUST BE C	JSR INCVEB JMP MORE CHANGED IF RELOCATED) LDA INH JSR PRTBYT JSR OUTSP JSR OUTSP JSR PRTPNT CLC LDA VEB+1 ADC POINTL
4 2 2 7 4 A A A C 2 2 2 2 2 2 5 2 8 1 9 A C 6	0 C 5 0 0 0 8 D 5	EA 28 (N F9 3B 9E 9E 1E	00 NOTE: 1E 1E 1E 1E	MUST BE C	JSR INCVEB JMP MORE CHANGED IF RELOCATED) LDA INH JSR PRTBYT JSR OUTSP JSR OUTSP JSR PRTPNT CLC LDA VEB+1 ADC POINTL STA POINTL
A A A A A C 2 2 2 2 2 5 2 8 1 A C C 6 8 0 A	0 C 5 0 0 0 0 8 D 5 5 D	EA 28 (N F 9 3 B 9 E 1 E E D F A E E	00 NOTE: 1E 1E 1E 1E	MUST BE C	JSR INCVEB JMP MORE CHANGED IF RELOCATED) LDA INH JSR PRTBYT JSR OUTSP JSR OUTSP JSR PRTPNT CLC LDA VEB+1 ADC POINTL STA POINTL LDA VEB+2
A A A A C 2 2 2 2 2 5 2 8 1 A A C B A A A A A A A A A A A A A A A C A A A C A	0 C 5 0 0 0 0 8 D 5 5 D 5	28 (NF9 3B 9E 1E ED FA EE FB	00 NOTE: 1E 1E 1E 1E	MUST BE C	JSR INCVEB JMP MORE CHANGED IF RELOCATED) LDA INH JSR PRTBYT JSR OUTSP JSR OUTSP JSR PRTPNT CLC LDA VEB+1 ADC POINTL STA POINTL LDA VEB+2 ADC POINTH
A A A C C 2 C F 2 2 2 2 5 1 9 A C C E 8 0 A 6 5 8 5 8	0 C 5 0 0 0 0 8 D 5 5 D 5 5	EA 28 (NF9 3B 9E 1E ED FA EE FB FB	00 NOTE: 1E 1E 1E 1E	MUST BE C	JSR INCVEB JMP MORE CHANGED IF RELOCATED) LDA INH JSR PRTBYT JSR OUTSP JSR OUTSP JSR PRTPNT CLC LDA VEB+1 ADC POINTL STA POINTL LDA VEB+2 ADC POINTH STA POINTH
A A A C 2 2 2 2 2 5 2 8 1 9 A A C E 8 0 A 6 5 8 8	0 C 5 0 0 0 0 8 D 5 5 D 5 5 9	28 (N F 9 3B 9E 1E ED FA EE FB 2D	00 NOTE: 1E 1E 1E 1E 1E 17	MUST BE C	JSR INCVEB JMP MORE CHANGED IF RELOCATED) LDA INH JSR PRTBYT JSR OUTSP JSR OUTSP JSR PRTPNT CLC LDA VEB+1 ADC POINTL STA POINTL LDA VEB+2 ADC POINTH STA POINTH LDA #'-
A A A A A A C 2 2 2 2 2 2 2 5 5 2 8 1 9 A C 6 E 8 0 A A 3 6 5 5 8 7 A 9 2	0 C 5 0 0 0 0 8 D 5 5 D 5 5 9 0	EA 28 F9 3B 9E ED FA EE FB FB 2D AO	00 NOTE: 1E 1E 1E 1E 17	MUST BE C	JSR INCVEB JMP MORE CHANGED IF RELOCATED) LDA INH JSR PRTBYT JSR OUTSP JSR PRTPNT CLC LDA VEB+1 ADC POINTL STA POINTL LDA VEB+2 ADC POINTH STA POINTH LDA #'- JSR OUTCH
A A A A A A C 2 2 2 2 2 2 2 2 5 5 2 8 1 9 A C 6 E 8 0 A A 3 6 5 8 7 A 9 2 C 2 2	0 C 5 0 0 0 0 8 D 5 5 D 5 5 9 0 0	28 (NF9 3B9E 1E ED FA EE FB FB 2D AO 1E	00 NOTE: 1E 1E 1E 1E 17	OUT	JSR INCVEB JMP MORE CHANGED IF RELOCATED) LDA INH JSR PRTBYT JSR OUTSP JSR OUTSP JSR PRTPNT CLC LDA VEB+1 ADC POINTL STA POINTL LDA VEB+2 ADC POINTH STA POINTH LDA #'- JSR OUTCH JSR PRTPNT
4 2 2 7 4 A A A C 2 2 5 2 2 2 5 5 2 8 1 9 A A C B A A A A A A A A A A A A A A A A	0 C 5 0 0 0 0 8 D 5 5 D 5 5 9 0 0 0	28 (NF9 3B9E 1E ED FA EE FB FB 2D AO 1E 2F	00 NOTE: 1E 1E 1E 17 17	MUST BE COOT	JSR INCVEB JMP MORE CHANGED IF RELOCATED) LDA INH JSR PRTBYT JSR OUTSP JSR PRTPNT CLC LDA VEB+1 ADC POINTL STA POINTL LDA VEB+2 ADC POINTH STA POINTH LDA #'- JSR OUTCH JSR PRTPNT JSR CRLF
4 2 2 7 4 A A A C C 2 2 2 2 5 5 2 1 8 9 A 6 6 E 8 0 A 6 5 7 A 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2	0 C 5 0 0 0 0 8 D 5 5 D 5 5 9 0 0	28 (NF9 3B9E 1E ED FA EE FB FB 2D AO 1E	00 NOTE: 1E 1E 1E 1E 17	OUT	JSR INCVEB JMP MORE CHANGED IF RELOCATED) LDA INH JSR PRTBYT JSR OUTSP JSR OUTSP JSR PRTPNT CLC LDA VEB+1 ADC POINTL STA POINTL LDA VEB+2 ADC POINTH LDA VEB+2 ADC POINTH LDA #'- JSR OUTCH JSR PRTPNT JSR CRLF JSR INTVEB
4 2 2 4 A A A A A A A C C 2 2 2 2 2 2 2 2 2 2 2	0 C 5 0 0 0 0 8 D 5 5 D 5 5 9 0 0 0 0 8	28 (NF9 3B9E 1E ED FA EE FB FB 2D AO 1E 2F	00 NOTE: 1E 1E 1E 17 17	OUT	JSR INCVEB JMP MORE CHANGED IF RELOCATED) LDA INH JSR PRTBYT JSR OUTSP JSR PRTPNT CLC LDA VEB+1 ADC POINTL STA POINTL LDA VEB+2 ADC POINTH STA POINTH LDA #'- JSR OUTCH JSR PRTPNT JSR CRLF
	C D D C C D D C C D D C C D D C C D D C C D D C C D D C C D D C C D D C C D D	C9 D0 20 C6 10 C9 C9 C9 C9 C8 C9 C9 C9 C9 C9 C9 C9 C9 C9 C9 C9 C9 C9	C9 16 D0 F3 20 24 C6 F9 10 F5 C9 2A D0 F1 20 F3 B 95 FC E8 30 F8 A 20 24 C9 2F F0 O2 E8 C9 C	C9 16 D0 F3 20 24 1A C6 F9 10 F5 C9 2A D0 F1 20 F3 19 20 F3 19 3 95 FC 6 E8 3 30 F8 3 20 24 1 A C9 2F F0 09	C9 16 TST D0 F3 20 24 1A C6 F9 10 F5 C9 2A D0 F1 A2 FD 20 F3 19 RD 3 95 FC 6 E8 6 30 F8 8 A2 02 MORE 3 20 24 1A SECOND C9 2F F F0 09

ZIPTAPE CASSETTE INTERFACE

(a review)

Wanna be able to load BASIC in 13 seconds? That's right - 13 seconds for an 8K load (about 12 times faster than HYPERTAPE). (600 bytes/sec).

As you can tell, I'm pretty enthusiastic about the cassette interface from Lew Edwards. far, this system has proved 100% reliable at 4800 baud. I use a Sankyo ST-50 cassette recorder.

This interface consists of a 2"x2" p.c. this interrace consists of a 2 x2 p.c. board using a single IC (needs 5 v. @ 10 ma.) and 346 bytes of driver software. It uses 3 bits (PAO, PAI, and PA2) of KIM's I/O, and from \$0200 to \$02A8 and \$0300 to \$03B2 of KIM's memory.

The documentation, which includes a full source listing of the driver software as well as a schematic of the hardware, comes with enough information to enable the user to get this system running on ANY 6502 system that has 3 bits of a 6530, 6532, 6520 or 6522 available for use.

This system can be operated at 2400 or 3600 baud if your recorder can't handle the full 4800 baud speed.

For \$26.50 you get an assembled interface board, a cassette of the software, and full documentation from Lew Edwards, 1451 Hamilton Ave., Trenton, N.J. 08629.

If you just can't swing a floppy-disc, Ziptape will ease the pain. - ERIC

CASSETTE AVAILABILITY

Are you looking for some high-quality short and medium length cassettes? AB Computers (POB 104, Perkasie, PA 18944 (215)257-8195) has some which come in 5-screw housings and use AGFA tape.

We use these cassettes for software distribution here at USER NOTES and have been quite satisfied with them. Here's the price list:

> Clo (5min/side) 10/\$6.25 C30 (15min/side) 10/\$8.00 plastic housings 10/\$1.00

EDITORIAL (continued from inside the cover)

Things we'd like to know: What boards have you used successfully in the KIMSI? What mods did you have to perform to get other boards operational? Has anyone figured out a way of modifying the KIMSI so that the special I/O port of the memory map is moved down into KIMS' 4K "black hole" (\$0400 \$13FF)?

MANUFACTURERS

Need some ideas for new products? The 44 pin KIMBUS is gaining in popularity now that Rockwell and Synertek have entered the marketplace with products intended to be used with the KIM-4. There's always room in the RAM board market, how bout a low-cost dynamic RAM board which can take advantage of the super low-cost 4116 which are being offered for the TRS-80 and APPLE machines. I've seen a set of eight going for as low as \$80.00. That's 16K!!! A good 64x16 or 80x24 video board is desperately needed.

How bout an EPROM board that can also program the 2708 or 2716. (At this point, the hobbyist is money ahead by sticking to the 2708, as low as \$5.00, unless he really needs the single voltage &f the Intel 2716.) A combination serial/ parallel board using the 6522 and maybe the new Synertek 6551 ACIA would be very popular (2P+2S?).

BASIC INCOMPATIBILITY

Microsoft has written versions of BASIC to run on all major 6502 machines (KIM, APPLE, PET and OSI.) Although, for the most part, a program written for one machine can be run on another machine if they are typed in, a memory image cannot be transferred from one type of machine to another (PET to KIM, for example). The reason? First of all, when you type a BASIC program into your computer (with Microsoft BASIC, anyway) the program is compressed by changing BASIC commands into

CONTINUED ON NEXT PAGE

KIM SOFTWARE ON CASSETTE

we know that you have better things to do with your time than punching hex code into your machine. Because of this, we have made some of the longer programs available on KIM cassette.

These cassettes are original dumps, not copies, made with top quality 5-screw housing cassettes. Thirty seconds of sync characters precede the program to enable you to tune up your recorder or PLL.

Are you AIM 8 SYM owners interested in having some of these programs available for your machines?

PAYMENT MUST BE IN U.S. FUNDS. OVERSEAS CUSTOMERS -- include \$1.00 extra per cassette for extra postage.

OUR PRESENT OFFERINGS INCLUDE:

KIMATH (specify \$2000 or \$F800 version)....\$12.00 (includes errata sheet for manual) HEXPAWN (from issue #13).....\$5.00 DISASSEMBLER (this issue).....\$5.00 RANNER (this issue).....\$5.00

6502 USER NOTES, POB 33093, N. ROYALTON OHIO page 26

"tokens". For example, if you type in 100 PRINT
"HI", BASIC would store two bytes for the address,
and one byte for PRINT. "HI" would be stored without change. Using one byte "tokens" lets you get
a larger BASIC program into smaller areas and could
even help them run faster. Only one problem:
Each different version of BASIC uses its own unique
'token' identifiers. (Does anyone know why this
is so?)

The only way to transfer BASIC programs from one type of 6502 machine to another is to "LIST" the program out to the other computer. In other words, instead of listing the BASIC program to your printer, the output would be "vectored" to a new output routine which would talk to your object computer. The object computer would also be running BASIC and it would expect its "input" from the first computer instead of its own keyboard. Tricky, bub?

The PET, for example, is set up to list a program to a device on its IEEE bus so if I wanted to transfer some BASIC programs from the PET to the KIM, I would hook the KIM up to the PET's IEEE bus and "list" the program to the KIM. Don't forget, KIM needs to have BASIC running and modified so that its input comes from the IEEE bus so that its interface instead of the terminal.

Such a PET to KIM BASIC interface is on my list of projects so it may get done in my life-time.

32K RAM FOR AROUND \$200

Those of you that are running KIM-4, or compatible, motherboards will be happy to hear that I now have in my hot little hands an article on how to build a 32K dynamic RAM board using the 4116 devices which are being used to expand the APPLE computer. (You've seen them in all the mags for \$80 - \$100 per 16K.) The RAM card contains its own built-in, invisible refresh circuit and can be built on a 4.5x6 size Vector wire wrap card.

According to the author -"In eight months of constant use with a KIM-1 and KIM-4, no problems of any kind have been encountered with the unit. A second unit, built at the end of 1978, also works well."

Sorry, you'll have to wait for the next issue for this one.

announcements and reviews

PRODUCT ANNOUNCEMENT

Tiny Editor/Assembler and Robot

If you only have 4K of expansion and want to assemble programs, (once you start assembling your programs, you'll never go back to hand assembly!) You may want more info on this tiny editor/assembler package. The flyer didn't mention what type of I/O device was supported or where the package was assembled to operate from, but the ROBOT language supports the TVT-6 and needs RAM expansion starting from \$0400 so the assembler requirements may be similar.

The single pass assembler overlays the editor in RAM and, except for the zero page references, seems to conform to the MOS definitions.

The price is \$23.00 for the user manual, commented source listing (\$20.00 without the cassette).

ROBOT is actually an interactive robot control language. The robot that is controlled is currently the cursor on the TVT-6 video board but it looks as if the user could modify this to con-

trol a "real" robot or a standard memory mapped video output device. ROBOT needs memory from \$0200-\$0540 and a TVT-6. I have this package and will be reassembling it to run an my system as soon as I get some time (fat chance!). This looks to be a very interesting package.

Several articles on an 8080 version have been published in Doctor Dobbs Journal.

ROBOT sells for \$8.00 and includes a user manual, commented source listing and a cassette (\$5.00 without the cassette). It's worth \$5.00 just to see how it works!

Contact Michael Allen, 6025 Kimbark, Chicago Ill 60637.

PRODUCT REVIEW of the HDE DISC SYSTEM by the editor

A number of you have asked for details about the HDE full size disc system.

The system is based around the SYKES $8\,^{\prime\prime}$ drive with the 6502 based intelligent controller.

This drive is soft sectored, IBM compatible, and single density which lets you store about a quarter megabyte of data on a disc.

The system software, called FODS (File Oriented Disc System), manages sequential files on the disc much the same way files are written on magnetic tape - one after another. When a file is deleted, from a sequentially managed file system, the space that the file occupied is not immediately reallocated, as in some disc operating systems. As it turns out, this can be an advantage as well as a disadvantage since deleted files on the FODS system can be recovered after the file has been (This has saved my sanity more than once!) Of course when you want to recover some of the disc space taken up by a number of these deleted files, you can simply re-pack or compress the disc and all the active files will be shifted down until there are no deleted files hanging around using up space.

FODS has this ability to repack a disc.

When saving and loading in FODS you work with named files, not track and sector data or I.D. bytes. This makes life alot easier. I've seen some disc systems where you have to specify track and sector info and/or I.D. bytes. What a pain that can be!

If you just want to save a source file temporarily, you can do that on what's known as "scratch-pads". There are two of these on a disc, "scratch-pade A" and "scratch-pad B", each of these temporary disc files can hold up to 16K or if "B" is not used, "A" can hold one file up to 32K in length. The only files that can be temporarily saved on scratch pad are files that have been built using the system text editor.

Being a dyed in the wool assembly language programmer, I really appreciate the FODS text editor! This line oriented editor is upwards compatible with the MOS/ARESCO editor but includes about everything you could aske for in a line editor. There is a full and semi-automatic line numbering feature, lines can be edited while they are being entered or recalled and edited later, strings can be located and substituted, the line numbers can be resequenced, the file size can be found, the hex address of a line can be known and comments can be appended to an assembly file after it has been found correct. Oops! I forgot to say lines can also be moved around and deleted. This isn't the complete list of FODS editor commands, just the ones that immediately come to mind.

Another very powerful feature of the system is the ability to actually execute a file containing a string of commands. For example, the newsletter mailing list is now being stored on disc. When I want to make labels, I would normally have to load each letter file and run the labels printing program. But with FODS, I can build up a "JOB" file of commands and execute it.



BOX 120 ALLAMUCHY, N.J. 07820 201-362-6574

HUDSON DIGITAL ELECTRONICS INC.

ANNOUNCING: COMPUTER PROGRAMS FOR THE KIM-1 HDE ASSEMBLER

An advanced, two pass assembler using 6502 cross-assembler mnemonics. Free form, line oriented entry. Directives include: .OPTION, .BYTE, .WORD, .FILE, .OFFSET, .END. Output options include LIST, NOLIST, SYMBOL TABLE, NO SYMBOL TABLE. GENERATE, NOGENERATE, ERRORS, NOERRORS, TAB, NOTAB, Assemble using single or multiple files. Place source, object and symbol table anywhere in memory, Automatic paging, with header and page number. Approximately 4K. Loads at E000 or 2000.

HDE TEXT OUTPUT PROCESSING SYSTEM (TOPS)

A comprehensive output processor, including left, right and full justification, variable page length, page numbering (Arabic, capital and lower case Roman), page titling, leading and trailing edge tabbing, field sequence modification, selective repeat, selective page output, etc. More than 30 commands to format and control output of letters, documents, manuscripts and textual material of all types. Approximately 4K. Loads at E100 or 2100.

HDE DYNAMIC DEBUGGING TOOL (DDT)

Built-in assembler/disassembler coupled with single step and dynamic breakpoint entry/deletion facilitates rapid isolation, correlation and test of programs. Keystrokes minimized with single letter, unshifted commands, and optional arguments. Approximately 2K. Loads at E000 or 2000.

WATCH FOR PRODUCT ANNOUNCEMENTS THIS YEAR TO INCLUDE:

- Dual Channel RS-232 interface with auto answer
- Eprom card, eprom programmer
- NEC, Diablo printer interface.

All HDE memory and interface cards are KIM-4 compatible in a 4½" X 6½" format with on-board 5 volt regulation and address selection switches. Complex circuits are socketed for ease of maintenance. All products include a 90 day full parts and labor warranty, except memory boards which are 6 months, and computer programs which have a limited warranty.

ORDER DIRECT OR FROM THESE FINE DEALERS:

Box 523 Medina, Ohio 44256 216-725-4560

JOHNSON COMPUTER | PLAINSMAN MICROSYSTEMS Box 1712 Auburn, Ala. 36830 800-633-8724

ARESCO P.O. Box 43 Audubon, Pa. 19407 215-631-9052